

0012

COLLABORATORS

| | | | |
|---------------|------------------------|------------------|------------------|
| | <i>TITLE :</i> 0012 | | |
| <i>ACTION</i> | <i>NAME</i> | <i>DATE</i> | <i>SIGNATURE</i> |
| WRITTEN BY | | January 16, 2023 | |

REVISION HISTORY

| NUMBER | DATE | DESCRIPTION | NAME |
|--------|------|-------------|------|
| | | | |

Contents

| | | |
|----------|--|----------|
| 1 | 0012 | 1 |
| 1.1 | Personal Fonts Maker - F. Selection of Amiga Printer Drivers | 1 |

Chapter 1

0012

1.1 Personal Fonts Maker - F. Selection of Amiga Printer Drivers

F. Selection of Amiga Printer Drivers

The following is a partial list of printers and some of the printer drivers which can be used in combination with those printers. Many drivers have been updated several times through the different versions of the Amiga operating system. Where the standard printer drivers provided with the Amiga operating system are not sufficient, at Cloanto we recommend alternate systems such as Studio and TurboPrint. Section 14.2 has more information on printers.

| Manufacturer | Printer | Driver | Note |
|--------------|----------------------|--|--------------|
| Alphacom | Alphapro 101 | Alphacom_Alphapro_101 | |
| Apple | Imagewriter | ImagewriterII | |
| Apple | Imagewriter II | ImagewriterII | |
| Brother | HR_15XL | Brother_HR-15XL | |
| Brother | xx09 and xx18 Series | EpsonX[CBM_MPS-1250] | (2) |
| Brother | xx24 Series | EpsonQ | (1) |
| Bull | Compuprint Series | EpsonX[CBM_MPS-1250] | (14) |
| CalComp | ColorMaster | CalComp_ColorMaster or CalComp_ColorMaster2 | (10) |
| Canon | PJ-1080A | Canon PJ-1080A | |
| Canon | Bubble Jet Printers | CanonBJ10 or CanonBJC | (13) (12) |
| CBM | MPS 1000 | CBM_MPS1000 | |
| CBM | MPS 1224 | Nec_Pinwriter | (3) |
| CBM | MPS 1250 | EpsonX[CBM_MPS-1250] | |
| CBM | MPS 1500 C | EpsonX[CBM_MPS-1250] or CBM_MPS1000 | (9) (8) |
| CBM | 6400 | Diablo_630 | (7) |
| CIE | CI-3500 | CBM_MPS1000 | (8) |
| CIE | L:ips 10 | EpsonX[CBM_MPS-1250] | (9) |
| Citizen | MSP Series | EpsonX[CBM_MPS-1250] | (2) |
| Citizen | Premier 35 | Diablo_630 | |
| Citizen | Swift Series | EpsonQ or Nec_Pinwriter | (1) (15) |
| Comrex | CR II and III | Brother_HR-15XL | |

| | | | |
|------------------|---------------------------|-----------------------------|------------|
| Diablo | 630 | Diablo_630 | |
| Diablo | Advantage D25 | Diablo_Advantage_D25 | |
| Diablo | C-150 | Diablo_C-150 | |
| Dynax | | Brother_HR-15XL | |
| Epson | LQ Series | EpsonQ | (1) |
| Epson | DX-20 | Diablo_630 | |
| Epson | EX,FX,JX,LX,MX,RX Series | EpsonX[CBM_MPS-1250] | (2) |
| Facit | x50 Series | EpsonX[CBM_MPS-1250] | (9) |
| Facit | x80 and x90 Series | EpsonQ | (1) |
| Fujitsu | DL Series | FujitsuDL | (12) |
| Fujitsu | Breeze Series | HP_DeskJet | (16) |
| Gemini | 10X | EpsonXOld | |
| Hewlett-Packard | DeskJet, Black and White | HP_DeskJet | (16) |
| Hewlett-Packard | DeskJet, Color | HP_DeskJet550C | (16) |
| Hewlett-Packard | LaserJet, All Series | HP_LaserJet | |
| Hewlett-Packard | PaintJet | HP_PaintJet | |
| Hewlett-Packard | ThinkJet | HP_ThinkJet | |
| Howtek | Pixelmaster | Howtek_Pixelmaster | |
| IBM | Proprinter | CBM_MPS1000 | |
| Juki | 5510 | EpsonX[CBM_MPS-1250] | (2) |
| Juki | 6000 | Diablo_630 | |
| Juki | 6100 | Diablo_630 | |
| Juki | 6300 | Diablo_630 | |
| Mannesmann Tally | MT Series | EpsonQ | (1) |
| NEC | CP2 and CP3 | EpsonX[CBM_MPS-1250] | (2) |
| NEC | P5,P6,P7,P9,CP6,CP7 | Nec_Pinwriter | (3) |
| NEC | P2, P6 and P7 Plus | Nec_Pinwriter | (3) |
| NEC | P2200, P60, P70 | Nec_Pinwriter | (3) |
| Oki | ML/Microline Series | EpsonQ | (1) |
| Okidata | 192 and 193 | CBM_MPS1000 | (8) |
| Okidata | 92 | Okidata_92 | |
| Okidata | 292 and 293 | Okidata_293I | (4) |
| Okidata | Okimate 20 | Okimate_20 | |
| Panasonic | KX-P 3131 and 3151 | Diablo_630 | |
| Panasonic | KX-P xx23 and xx24 Series | EpsonQ | (1) |
| Panasonic | 1080, 1091, 1092, 1592 | EpsonX[CBM_MPS-1250] | (2) |
| Philips | PP 40x Series | EpsonQ | (1) |
| Quadram | QuadJet | Quadram_QuadJet | |
| Qume | LetterPro 20 | Qume_LetterPro_20 | |
| Qume | Sprint2 | Diablo_630 | |
| Samsung | SP-24xx Series | EpsonQ | (1) |
| Seiko | 5301, 5303 and 5312 | Seiko_5300 | (11) |
| Seikosha | BP, SBP, SP and SL 532 | EpsonX[CBM_MPS-1250] | (2) |
| Seikosha | SL and LT Series | EpsonQ | (1) |
| Star | NL, NX, ND, NR | EpsonXOld or CBM_MPS1000 | (9) (8) |
| Star | LC-10, FR-10 | EpsonX[CBM_MPS-1250] | (2) |
| Star | NB24, LC24, XB24 | EpsonQ | (1) |
| TEC | F10 | Diablo_630 | |
| Tektronix | 4696 | Tektronix_4696 | (12) |
| Tektronix | 4693D | Tektronix_4693D | (12) |
| Toshiba | P351 C, 341 and 1340 | Toshiba_P351C | (5) |
| Toshiba | P351 SX | Toshiba_P351SX | (6) |
| Toshiba | P321 SL and SLC | Toshiba_P351SX | (6) |
| Toshiba | P341 SL and SLC | Toshiba_P351SX | (6) |
| Triumph Adler | TA MPR Series | EpsonQ | (1) |
| Xerox | 4020 | Xerox_4020 | |

Notes:

- (1) For Epson 24/48-pin printers and compatibles (360 by 360 dpi graphics). Compatible printers must be set in the Epson LQ or ESC/P2 emulation mode. Also works well in text mode on 8/9-pin printers.
 - (2) For Epson 8/9-pin printers and compatibles. Compatible printers must be set in the Epson X emulation mode. Better results in both text and graphics mode may be obtained using the EpsonXOld driver. The EpsonQ driver should be used for 24-pin printers.
 - (3) For NEC Pinwriter 24-pin printers and compatibles. Compatible printers must be set in the NEC Pinwriter emulation mode.
 - (4) The IBM interface module is required.
 - (5) Drives all Toshiba P351 C and compatibles.
 - (6) Drives all Toshiba P351 SX and compatibles.
 - (7) The Centronics option is required.
 - (8) The printer must be in IBM mode to use the CBM_MPS1000 driver. Some functions may not be activated.
 - (9) To use the EpsonX driver, the printer must be in Epson mode. Some features may not be supported. Note (2) also applies.
 - (10) The CalComp_ColorMaster driver should be used on systems with less than 1 Mbyte of RAM. The CalComp_ColorMaster2 driver is faster, but uses more memory. Both drivers also work with the CalComp ColorView printer.
 - (11) The Seiko_5300a driver is also available. The Seiko_5300a is faster than the standard Seiko_5300, but it requires more memory. Note (12) also applies.
 - (12) These drivers are not included on the Workbench and Extras disks. They may be available from the printer manufacturer, in Amiga disk collections (e.g. Fish Disk) and electronic networks (e.g. Internet/Aminet, CompuServe, BIX).
 - (13) New drivers introduced with version 2.1 of the Amiga operating system.
 - (14) Tests have shown that 9-pin Epson drivers may yield better printouts than IBM and EpsonQ drivers even on 24-pin printers. Note 9 may also apply.
 - (15) The improved Print Manager Amiga drivers are available from Citizen. Note 3 also applies.
 - (16) New drivers developed by Commodore and Cloanto.
-