

# Negative System Error Codes

## System Errors (VBL Mgr, Queue, Etc.)

0	noErr	0 for success *OR*
0	smNotTruncated	No truncation necessary
-1	qErr	

queue element not found during deletion

		*OR*
-1	smTruncErr	Truncation indicator alone is wider than the specified width
-2	vTypErr	invalid queue element
-3	corErr	core routine number out of range
-4	unimpErr	unimplemented core routine
-5	SlpTypeErr	invalid queue element
-8	seNoDB	no debugger installed to handle debugger command

## Color Manager Errors

-9	iTabPurgErr	from Color2Index/ITabMatch
-10	noColMatch	from Color2Index/ITabMatch
-11	qAllocErr	from Make1Table
-12	tblAllocErr	from Make1Table
-13	overRun	from Make1Table
-14	noRoomErr	from Make1Table
-15	seOutOfRange	from SetEntry
-16	seProtErr	from SetEntry
-17	i2CRangeErr	from SetEntry
-18	gdBadDev	from SetEntry
-19	reRangeErr	from SetEntry
-20	seInvRequest	from SetEntry
-21	seNoMemErr	from SetEntry

## I/O System Errors

-17	controlErr	Driver can't respond to Control call
-18	statusErr	Driver can't respond to Status call
-19	readErr	Driver can't respond to Read call
-20	writErr	Driver can't respond to Write call
-21	badUnitErr	Driver ref num doesn't match unit table
-22	unitEmptyErr	Driver ref num specifies NIL handle in unit table
-23	openErr	Requested read/write permission doesn't match drivers open permission, or Attempt to open RAM serial Driver failed
-24	closErr	Close failed; Permission to close .MPP driver was denied
-25	deRemovErr	DrvrInstall couldn't find driver in resources
-27	abortErr	IO call aborted by Kill10; Publisher has written a new edition *OR*
-27	iLoAbortErr	IO abort error (Printing Manager)
-28	notOpenErr	Couldn't rd/wr/ctl/sts cause driver not opened
-29	unitTblFullErr	Unit table has no more entries
-30	dceExtErr	dce extension error

## File System Errors

-33	dirFulErr	Directory full
-34	dskFulErr	Disk Full
-35	nsvErr	No such volume; volume not found
-36	ioErr	I/O error (bummers)
-37	bdNamErr	Bad file name; there may be no bad names in the final system!
-38	fnOpnErr	File not open
-39	eofErr	End of file; no additional data in the format
-40	posErr	Tried to position to before start of file (r/w)
-42	tmfoErr	too many files open
-43	fnfErr	File not found; Folder not found; Edition container not found; Target not found
-44	wPrErr	Diskette is write protected; Volume is locked through hardware
-45	fLckdErr	File is locked
-45	fLckdErr	Publisher writing to an edition
-46	vLckdErr	Volume is locked through software
-47	fBsyErr	

```

        File is busy (delete); Section doing I/O
-48
    dupFNerr
        Duplicate filename (rename); File found
            instead of

                folder

-49
    opWrErr
        File already open with with write permission
-50
    paramErr
Error in user parameter list
-51    rfNumErr        Reference number invalid
-52    gfpErr         Get file position error
-53    volOffLinErr   Volume is off line
-54    permErr        Software lock on file; Not a subscriber
                    [permissions error on file open]
-55    volOnLinErr    drive volume already on-line at MountVol
-56    nsDrvErr       no such drive (tried to mount a bad drive num)
-57    noMacDskErr    not a mac diskette (sig bytes are wrong)
-58    extFSErr       External file system - file system identifier
                    is nonzero
-59    fsRnErr        file system internal error: during rename the
                    old entry was deleted but could not be
                    restored...

-60    badMDBErr      bad master directory block
-61    wePermErr      Write permissions error; Not a publisher

```

#### Font Manager Errors

```

-64    fontDecError   error during font declaration
-65    fontNotDeclared font not declared
-66    fontSubErr     font substitution occurred

```

#### Disk, Serial Port, Clock Specific Errors

```

-64    lastDskErr     drive not installed
-64    noDriveErr     drive not installed
-65    offLinErr      r/w request for an off-line drive
-66    noNybErr       couldn't find 5 nybbles in 200 tries
-67    noAdrMkErr     couldn't find valid addr mark
-68    dataVerErr     read and verify compare failed
-69    badCksmErr     addr mark checksum didn't check
-70    badBtSlpErr    bad addr mark bit slip nibbles
-71    noDtaMkErr     couldn't find a data mark header
-72    badDCKsum      bad data mark checksum
-73    badDBtSlp     bad data mark bit slip nibbles
-74    weUnderrun     write underrun occurred
-75    cantStepErr    step handshake failed
-76    tkOBadErr      track 0 detect doesn't change
-77    initIWMerr     unable to initialize IWM
-78    twoSideErr     tried to read 2nd side on a 1-sided drive
-79    spdAdjErr      unable to correcetly adjust disk speed
-80    seekErr        track number wrong on address mark
-81    sectNFErr      sector number never found on a track

```

-82	fmt1Err	can't find sector 0 after track format
-83	fmt2Err	can't get enough sync
-84	verErr	track failed to verify
-84	firstDskErr	
-85	clkRdErr	unable to read clock value twice
-86	clkWrErr	time written did not verify
-87	prWrErr	parameter ram written didn't read-verify
-88	prInitErr	InitUtil found the parameter ram uninitialized
-89	rcvrErr	SCC receiver error (framing, parity, OR)
-90	breakRecd	Break received (SCC)

#### AppleTalk Errors

-91	ddpSktErr	Error opening socket *OR*
-91	eMultiErr	Invalid address or table is full
-92	ddpLenErr	Data lenth too big *OR*
-92	eLenErr	Packet too large or first entry of the write data structure did not contain the full 14-byte header
-93	noBridgeErr	No router available [for non-local send]
-94	lapProtErr	error in attaching/detaching protocol *OR*
-94	LAPProtErr	Protocol handler is already attached, node's protocol table is full, protocol not attached, or protocol handler pointer was not 0
-95	exceedsCollsns	

Hardware error [excessive collusions on write]

-97	portInUse	driver Open error code (port is in use)
-98	portNotCf	driver Open error code (parameter RAM not configured for this connection)
-99		

memROZEErr

hard error in ROZ  
-99

memROZError

hard error in ROZ  
-99 memROZWarn

soft error in ROZ

Scrap Manager Errors

-100

noScrapErr

No scrap exists error  
-102

noTypeErr

Format not available [no object of that type

in scrap]

Storage Allocator Errors

-108

memFullErr

Ran out of memory [not enough room in heap

zone]  
-109

noHandleErr

GetHandleSize fails on baseText or

substitutionText; NIL master pointer [handle  
was NIL in HandleZone or other]  
-110

memAdrErr

Address was odd, or out of range  
-111

memWZErr

Attempted to operate on a free block;  
GetHandleSize fails on baseText or  
substitutionText [WhichZone failed (applied to  
free block)]  
-112

memPurErr

Trying to purge a locked or non-purgeable

block  
-113

memAZErr           Address in zone check failed  
-114

memPCErr



Pointer Check failed  
-115

memBCErr

Block Check failed  
-116 memSCErr           Size Check failed  
-117 memLockedErr       Trying to move a locked block (MoveHHI)

#### HFS Errors

-120 dirNFErr  
Directory not found  
-121 tmwdoErr

No free WDCB available  
-122

badMovErr

Move into offspring error  
-123

wrgVolTypErr

Not an HFS volume [wrong volume type error

or (obsolete) operation not supported for

MFS]  
-124

volGoneErr

Server volume has been disconnected  
-125

updPixMemErr

Insufficient memory to update a pixmap  
-127

fsDSIntErr

Internal file system error

[Menu Manager Errors](#)

-126

dsMBarNFnd

System error code for MBDF not found  
-127

dsHMenuFindErr

Could not find Hmenu's parent in MenuKey  
-128

userCanceledErr

User canceled an operation

HFS File ID Errors

-130

fidNotFound

no file thread exists  
-131

fidNotAFile

directory specified  
-132

fidExists

file id already exists

Color QuickDraw & Color Manager Errors

-147

regionTooBigError  
Region too big or complex  
-148

pixmapTooBigErr

Pixel map record is deeper than 1 bit per

pixel [passed pixelmap is too large]  
-149

notEnoughStack

Not enough stack space for the necessary

buffers \*OR\*

-149

mfStackErr

Insufficient stack

-150

cMatchErr

Color2Index failed to find an index

-151

cTempMemErr

Failed to allocate memory for temporary

structures  
-152

cNoMemErr



Failed to allocate memory for structure  
-153

cRangeErr

Range error on colorTable request  
-154

cProtectErr

ColorTable entry protection violation  
-155

cDevErr

Invalid type of graphics device  
-156

cResErr

Invalid resolution for MakelTable  
-157

cDepthErr

Invalid pixel depth  
-158

cParmErr

Invalid parameter

## Resource Manager Errors (other than I/O Errors)

-185

badExtResource

Extended resource has a bad format

-186

CantDecompress

Resource bent ("the bends")

-188

resourceInMemory

Resource already in memory

-189

writingPastEnd

Writing past end of file

-190

inputOutOfBounds

Offset or count out of bounds

-192    resNotFound

Resource not found  
-193 resFnotFound

Resource file not found  
-194

addResFailed

AddResource failed  
-195

addRefFailed

Add Reference failed  
-196

rmvResFailed

RmveResource failed  
-197

rmvRefFailed

RMVReference failed  
-198

resAttrErr

Attribute inconsistent with operation  
-199

mapReadErr

Map inconsistent with operation

[Sound Manager Errors](#)

-200

noHardware

Required sound hardware not available [no

hardware support for the specified

synthesizer]  
-201

notEnoughHardware

Insufficient hardware available [no more

channels for the specified synthesizer  
-203

queueFull

No room in the queue  
-204

resProblem

Problem loading the resource  
-205

badChannel

Channel is corrupt or unusable [invalid



channel queue lenth]  
-206

badFormat

Resource is corrupt or unusable  
-207

notEnoughBufferSpace  
Insufficient memroy available  
-208

badFileFormat

File is corrupted or unusable, or not AIFF

or AIFF-C  
-209

channel

Channel is busy

-210

buffersTooSmall

Buffer is too small

-211

channelNotBusy

Channel not currently used

-212

noMoreRealTime

Not enough CPU time available

-213

badParam

A parameter is incorrect  
-220

siNoSoundInHardware  
No sound input hardware available  
-221

siBadSoundInDevice  
Invalid sound input device  
-222

siNoBufferSpecified  
No buffer specified  
-223

siInvalidCompression  
Invalid compression type  
-224

siHardDiskTooSlow  
  
Harddrive too slow to record  
-225

siInvalidSampleRate  
Invalid sample rate  
-226

siInvalidSampleSize  
Invalid sample size  
-227

siDeviceBusyErr

Sound input device is busy  
-228

siBadDevice Name

Invalid device name  
-229

siBadRefNum

Invalid reference number  
-230

siInputDeviceErr

Input device hardware failure  
-231

siUnknownInfoType

Unknown type of information  
-232

siUnknownQuality

Unknown quality

## MIDI Manager Errors

-250

midiNoClientErr

no client with that ID found  
-251

midiNoPortErr

no port with that ID found  
-252

midiTooManyPortsErr  
too many ports already installed in the

system  
-253

midiTooManyConsErr

to many connections made  
-254

midiVConnectErr

pending virtual connection created  
-255

midiVConnectMade

pending virtual connection resolved  
-256

midiVConnectRmvd

pending virtual connection removed  
-257

midiNoConErr

no connection exists between specified

ports  
-258

midiWriteErr



couldn't write to all connected ports  
-259

midiNameLenErr

name supplied is longer than 31

characters  
-260

midiDuplDErr

duplicate client ID  
-261

midiInvalidCmdErr

command not supported for port type

Notification Manager Errors

-299

nmTypeErr

Invalid qType-must be ORD(nmType)

Start Manager Errors

-290

smSDMInitErr

SDM could not be initialized  
-291

smSRTInitErr

Slot Resource Table could not be

initialized  
-292

smPRAMInitErr

Slot Resource Table could not be

initialized  
-293

smPriInitErr

Cards could not be initialized  
-300

smEmptySlot

No card in slot  
-301

smCRCFail

CRC check failed for declaration data  
-302

smFormatErr

FHeader Format is not Apple's  
-303

smRevisionErr

Wrong revision level  
-304

smNoDir

Directory offset is Nil  
-305

smLWTstBad

Long Word test field <> \$5A932BC7  
-306

smNosInfoArray

No sInfoArray. Memory Mgr error.  
-307

smResrvErr

Fatal reserved error. Reserved field <>

0.  
-308

smUnExBusErr

Unexpected Bus Error  
-309

smBLFieldBad

ByteLanes field was bad.  
-310

smFHBlockRdErr

Error occurred during \_sGetFHeader  
-311

smFHBlkDispErr



Error occurred during \_sDisposePtr

(Dispose of  
FHeader block).  
-312

smDisposePErr

\_DisposePointer error  
-313

smNoBoardsRsrc

No Board sResource  
-314

smGetPERR

Error occurred during \_sGetPRAMRec (See

SIMStatus)  
-315

smNoBoardId

No board Id  
-316

smIntStatVErr

The initStatusV field was negative after

primary or secondary init.  
-317

smIntTbleVErr

An error occurred while trying to

initialize the Slot Resource Table.  
-318

smNoJumpTbl

SDM jump table could not be created.  
-319

smBadBoardId

BoardId was wrong, re-init the PRAM

record.  
-320

smBusErrTO

BusError time out.  
-330

smBadRefld

Reference Id not found in list  
-331

smBadsList

Bad sResource [sList] structure:

Id1<Id2<Id3 ... format is not followed.  
-332

smReservedErr

Reserved field not zero  
-333

smCodeRevErr

Code revision is wrong  
-334

smCPUErr

Code revision is wrong  
-335

smsPointerNil

LPointer is nil From sOffset Data. If



this error occurs, check sInfo rec for

more information  
-336

smNilsBlockErr

Nil sBlock error Don't allocate and try

to use a nil sBlock

-337

smSlotOOBErr

Slot out of bounds error  
-338

smSelOOBerr

Selector out of bounds error; function

not  
implemented

-339

smNewPErr

\_NewPtr error  
-340

smBlkMoveErr

\_BlockMove error  
-341

smCkStatusErr

Status of slot = fail  
-342

smGetDrvrNamErr

Error occurred during \_sGetDrvrName  
-343

smDisDrvrNamErr

Error occurred during \_sDisDrvrName  
-344

smNoMoresRsrcs

No more sResources \*OR\*  
-344

smNoMoresResources  
Specified sResource data structure not

found  
-345

smsGetDrvrErr

Error occurred during \_sGetDriver  
-346

smBadsPtrErr

Bad pointer was passed to sCaldsPointer

function  
-347

smByteLanesErr

ByteLanes field in card's format block

was  
determined to be zero  
-348

smOffsetErr

Offset was too big (temporary, should be

fixed)  
-349

smNoGoodOpens

No opens were successful in the loop  
-350



smSRTOvrFlErr

SRT over flow  
-351

smRecNotFnd

Record not found in the SRT

Misc. Device Manager Errors

-360

slotNumErr

invalid slot # error  
-400

gcrOnMFMErr



-472

scsiTransferErr

write flag conflicts with data transfer

phase

-473

scsiBusTOErr

bus error during transfer

-474

scsiSelectTOErr

scsiSelTO exceeded (selection failed)

-475

scsiTimeOutErr

scsiReqTO exceeded

-476

scsiBusResetErr

the bus was reset, so your request was

aborted  
-477

scsiBadStatus

non-zero (not "Good") status returned  
-478

scsiNoStatusErr

device did not go through a status phase  
-479

scsiLinkFailErr

linked command never executed  
-489

scsiUnimpVctErr

unimplemented routine was called

Debugger Errors  
(SysErrs used instead of inline \$A9FF & \$ABFF)

-490

userBreak

user debugger break  
-491

strUserBreak

user debugger break - display string on

stack  
-492

exUserBreak

user debugger break - execute commands on

stack

Misc. QuickDraw, TextEdit and O/S Errors

-500

rgnTooBigErr

Bitmap would convert into a region

greater than 64 KB  
-501

teScrapSizeErr

scrap item too big for text edit record  
-502

hwParamrErr

bad selector for \_HWPriv

#### Process Manager Errors

-600

procNotFound  
No eligible process with specified process

serial number  
-601

memFragErr  
Not enough room to launch application

with special requirements  
-602

appModeErr  
Memory mode is 32-bit, but application is

not 32-bit clean  
-603

protocolErr  
app made module calls in improper order  
-604

hardwareConfigErr  
hardware configuration not correct for call  
-605

appMemFullErr  
Partition size specified in 'SIZE'



resource is not big enough for launch  
-606

appIsDaemon  
Application is background-only  
-607

bufferIsSmall  
Buffer is too small  
-608

noOutstandingHLE  
No outstanding high-level event  
-609

connectionInvalid Connection is invalid  
-610

noUserInteractionAllowed Attempted PostHighLevelEvent from

background and no session yet

established

### Virtual Memory Dispatch Errors

-620

notEnoughMemoryErr Insufficient physical memory  
-621

notHeldErr Specified range of memory is not held  
-622

cannotMakeContiguousErr Cannot make specified range

contiguous

-623

notLockedErr           Specified range of memory is not locked

-624

interruptsMaskedErr   Called with interrupts masked

-625

cannotDeferErr        Unable to defer additional user functions

#### Database Access (PACK13) Errors

-800

rcDBNull

The data item was NULL

-801

rcDBValue

Data available or successfully retrieved

-802

rcDBError

Error executing function

-803

rcDBBadType

Next data item not of requested data type

-804

rcDBBreak

Function timed out

-805

rcDBExec

Query currently executing

-806

reDBBadSessID

Session ID is invalid

-807

rcDBBadSessNum  
Invalid session number  
-808

rcDBBadDDEV  
Couldn't find the specified database

extension,  
or error occurred in opening

database extension  
-809

rcDBAsyncNotSupp  
The database extension does not support

asynchronous calls  
-810

rcDBBadAsyncPB  
Invalid parameter block specified  
-811

rcDBNoHandler  
There is no handler for this data type

installed for the current application  
-812

rcDBWrongVersion  
Wrong version number  
-813

rcDBPackNotInited  
The InitDBPack function has not yet been called

#### [Balloon Help Manager Errors](#)

-850

hmHelpDisabled      Help balloons are not enabled

-851

hmResNotFound        ????  
-852

hmMemFullErr         ????  
-853

hmBalloonAborted    Because of constant cursor movement,  
  the help balloon wasn't displayed  
-854

hmSameAsLastBalloon Menu and item are same as previous menu

and item  
-855

hmHelpManagerNotInited Help menu not set up  
-856

hmBadSelector         ????  
-857

hmSkippedBalloon      No ballon content to fill in  
-858

hmWrongVersion        Wrong version of Help Manager resource  
-859

hmUnknownHelpType    Help message record contained a bad type  
-860

hmCouldNotLoadPackage    ???  
-861

hmOperationUnsupported    Bad method parameter  
-862

hmNoBalloonUp         No balloon showing  
-863

hmCloseViewActive  
User using Close View won't let you

remove  
balloon

#### AppleTalk PPC Toolbox Errors

-900

notInitErr

PPC Toolbox has not been initialized yet  
-902

nameTypeErr

Invalid or inappropriate



locationKindSelector  
in location name  
-903

noPortErr

Invalid port name; Unable to open port or

bad port reference number  
-904

noGlobalsErr

System unable to allocate memory,

critical error  
-905

localOnlyErr

Network activity is currently disabled  
-906

destPortErr

Port does not exist at destination  
-907

sessTableErr

PPC Toolbox is unable to create a session  
-908

noSessionErr

Invalid session reference number  
-909

badReqErr

Bad parameter or invalid state for this

operation  
-910

portNameExistsErr  
Another port is already open with this

name  
-911

noUserNameErr

User name unknown on destination machine  
-912

userRejectErr

Destination rejected the session request  
-915

noResponseErr

Unable to contact application  
-916

portClosedErr

The port was closed  
-917

sessClosedErr

The session has closed  
-919

badPortNameErr

PPC port record is invalid  
-922

noDefaultUserErr

User has not specified owner name in

Sharing Setup control panel  
-923

notLoggedInErr

Default user reference number does not

yet exist  
-924

noUserRefErr

Unable to create a new user reference

number  
-925

networkErr

An error has occurred in the network  
-926

noInformErr

PPCStart failed because target

application did

not have an inform pending  
-927

authFailErr

User's password is wrong  
-928



noUserRecErr           Invalid user reference number  
-930

badServiceMethodErr   Service method is other than

ppcServiceRealTime  
-931

badLocNameErr         Location name is invalid  
-932

guestNotAllowedErr   Destination port requires authentication

#### AppleTalk NBP Errors

-1024

nbpBuffOvr

Buffer overflow in LookupName  
-1025

nbpNoConfirm

Name not confirmed on ConfirmName  
-1026

nbpConfDiff

Name confirmed at different socket  
-1027

nbpDuplicate

Duplicate name exists already  
-1028

nbpNotFound

Name not found on remove  
-1029

nbpNISErr

Error trying to open the NIS

AppleTalk ASP (XPP Driver) Errors

-1066

aspBadVersNum

Server cannot support this ASP version  
-1067

aspBufTooSmall

Buffer too small  
-1068

aspNoMoreSess

No more sessions on server  
-1069

aspNoServers

No servers at that address  
-1070

aspParamErr

Parameter error  
-1071

aspServerBusy

Server cannot open another session  
-1072

aspSessClosed

Session closed  
-1073

aspSizeErr

Command block too big  
-1074

aspTooMany

Too many clients (server error)  
-1075

aspNoAck

No ack on attention request (server err)

[AppleTalk ATP Errors](#)

-1096

reqFailed

Request to contact router failed: retry

count exceeded  
-1097

tooManyReqs

Too many concurrent requests  
-1098

tooManySkts

Too many concurrent responding-sockets  
-1099

badATPSkt

Bad ATP-responding socket  
-1100

badBuffNum

Bad response buffer number specified  
-1101

noRelErr

No release received  
-1102

cbNotFound

Control Block not found; no pending

asynchronous calls  
-1103

noSendResp

AddResponse issued without SendResponse  
-1104

noDataArea

No data area for request to MPP  
-1105

reqAborted

ERdCancel function called for this ERead

[SendRequest aborted by RelTCB]

[AppleTalk DSP Errors](#)

-1273

errOpenDenied

Open request denied by recipient  
-1274

errDSPQueueSize

Send or receive queue is too small  
-1275

errFwdReset

Read terminated by forward reset  
-1276

errAttention

Attention message too long  
-1277

errOpening

Attempt to open connection failed  
-1278

errState

Bad connection state for this operation  
-1279

errAborted

Request aborted by dspRemove or dspClose

function  
-1280

errRefNum

Bad connection reference number

#### New HFS Errors

-1300

fidNotFound

File ID not found [No file thread exists]  
-1301

fidExists

File id already exists  
-1302

notAFileErr

Specified file is a directory  
-1303

diffVolErr

Files on different volumes  
-1304

catChangedErr

Catalog has changed and CatPosition may be

invalid  
-1305

desktopDamagedErr The desktop database has become corrupted -

the Finder will fix this, but if your



application is not running with the Finder,

use DTReset or DTDelete

[AppleEvent Errors](#)

-1700  
errAECOercionFail Data could not be coerced to the  
requested descriptor type  
-1701  
errAEDescNotFound Descriptor record was not found  
-1702  
errAECorruptData Data in an Apple event could not be read  
-1703  
errAEWrongDataType Wrong descriptor type  
-1704  
errAENotAEDesc Not a valid descriptor record  
-1705  
errAEBadListItem Operation involving a list item failed  
-1706  
errAENewerVersion Need a newer version of the Apple Event

#### Manager

-1707  
errAENotAppleEvent Event is not an Apple event  
-1708  
errAEEventNotHandled Event wasn't handled by an Apple event

handler  
-1709  
errAEReplyNotValid AEResetTimer was passed an invalid reply  
-1710  
errAEUnknownSendMode Invalid sending mode was passed  
-1711  
errAEWaitCanceled User canceled out of wait loop for reply  
or receipt  
-1712  
errAETimeout Apple event timed out  
-1713  
errAENoUserInteraction No user interaction allowed  
-1714  
errAENotASpecialFunction Wrong keyword for a special function  
-1715  
errAEParamMissed Handler did not get all required paramters  
-1716  
errAEUnknownAddressType Unknown Apple event address type  
-1717  
errAEHandlerNotFound No handler found for an Apple event  
  
or a coercion  
-1718  
errAEReplyNotArrived Reply has not yet arrived  
-1719

errAEIllegalIndex    Not a valid list index

AppleTalk - ATP Errors

-3101

buf2SmallErr

Packet too large for buffer; partial data

returned

-3102

noMPPErr

No MPP error  
-3103

ckSumErr

Check sum error  
-3104

extractErr

Extraction error  
-3105

readQErr

Read queue error  
-3106

atpLenErr

ATP length error  
-3107

atpBadRsp

ATP bad response error  
-3108

recNotFnd

Record not found

-3109

sktClosedErr

Socket closed error

Print Manager with LaserWriter Errors

-4096

???

No free Connect Control Blocks available  
-4097

???

Bad connection reference number  
-4098

???

Request already active  
-4099

???

Write request too big  
-4100

???

Connection just closed  
-4101

???

Printer not found, or closed

#### File Manager Extension and AppleTalk AFP Errors

-5000       accessDenied  
          Incorrect access for this file/folder  
-5006

DenyConflict

Permission/Deny mode conflicts with the

current mode in which this fork is already

open  
-5015

NoMoreLocks

Byte range locking failure from Server  
-5020

RangeNotLocked

Attempt to unlock an already unlocked



range  
-5021

RangeOverlap

Attempt to lock some of an already locked

range  
APPLETALK AFP ERRORS

-5000

afpAccessDenied    AFP Access denied  
-5001

afpAuthContinue    AFP Authorization continue  
-5002

afpBadUAM            AFP Bad UAM  
-5003

afpBadVersNum      AFP Bad version number  
-5004

afpBitmapErr        AFP Bit map error  
-5005

afpCantMove -5006	AFP Can't move error
afpDenyConflict -5007	AFP Deny conflict
afpDirNotEmpty -5008	AFP Dir not empty
afpDiskFull -5009	AFP Disk full
afpEofError -5010	AFP End-of-File error
afpFileBusy -5011	AFP File busy
afpFlatVo -5012	AFP Flat volume
afpItemNotFound -5013	AFP Information not found
afpLockErr -5014	AFP Lock error
afpMiscErr -5015	AFP Misc error

afpNoMoreLocks	AFP No more locks
-5016	
afpNoServer	AFP No server
-5017	
afpObjectExists	AFP Object already exists
-5018	
afpObjectNotFound	AFP Object not found
-5019	
afpParmErr	AFP Parm error
-5020	
afpRangeNotLocked	AFP Range not locked
-5021	
afpRangeOverlap	AFP Range overlap
-5022	
afpSessClosed	AFP Session closed
-5023	
afpUserNotAuth	AFP User not authorized
-5024	
afpCallNotSupported	AFP Call not supported
-5025	

afpObjectTypeErr AFP Object type error  
-5026

afpTooManyFilesOpen AFP Too many files open  
-5027

afpServerGoingDown AFP Server going down  
-5028

afpCantRename AFP Can't rename  
-5029

afpDirNotFound AFP Directory not found  
-5030

afpIconTypeError Size of new icon and one it replaces don't

match  
-5031

afpVolLocked        Volume is Read-Only  
-5032

afpObjectLocked    Object is M/R/D/W inhibited

[See next Chapter for more negative I.D. codes.](#)