

LJ4Boost

Oliver Hitz

COLLABORATORS

	<i>TITLE :</i> LJ4Boost		
<i>ACTION</i>	<i>NAME</i>	<i>DATE</i>	<i>SIGNATURE</i>
WRITTEN BY	Oliver Hitz	August 23, 2022	

REVISION HISTORY

NUMBER	DATE	DESCRIPTION	NAME

Contents

1	LJ4Boost	1
1.1	Welcome to LJ4Boost Printer Driver Package	1
1.2	Disclaimer	2
1.3	Copyright And Distribution	2
1.4	Package Contents	3
1.5	Introduction	3
1.6	Features	3
1.7	Requirements	4
1.8	Compatibility	4
1.9	Installation	4
1.10	Installation Of The Printer Driver	5
1.11	Using The Printer Driver	5
1.12	Escape Sequences	6
1.13	ANSI Mode	9
1.14	HP/GL-2 Mode	10
1.15	Installation Of The Preferences Editor	10
1.16	Getting Started	10
1.17	FROM	11
1.18	CREATEICONS YES	11
1.19	CREATEICONS NO	12
1.20	EDIT/S	12
1.21	USE/S	12
1.22	SAVE/S	12
1.23	PUBSCREEN/K	12
1.24	Using The Preferences Editor	12
1.25	Copies	13
1.26	Paper Feed	14
1.27	Econo Mode	14
1.28	Auto Continue	14
1.29	Density	14

1.30 Image Adapt	14
1.31 Page Protect	14
1.32 REt	15
1.33 Compression	15
1.34 Save	15
1.35 Use	15
1.36 Cancel	15
1.37 Open...	15
1.38 Save As...	16
1.39 About	16
1.40 Quit	16
1.41 Reset To Defaults	16
1.42 Last Saved	16
1.43 Restore	16
1.44 Create Icons?	16
1.45 Hints	17
1.46 Compression And Speed	17
1.47 Known Problems	17
1.48 Troubleshooting	17
1.49 Registration	18
1.50 Updates	18
1.51 FriByte BBS located in Fribourg/Switzerland	19
1.52 Feedback	19
1.53 How To Reach The Author	19
1.54 History	20
1.55 Future	20

Chapter 1

LJ4Boost

1.1 Welcome to LJ4Boost Printer Driver Package

LJ4Boost

An Amiga printer driver especially designed for
Hewlett-Packard LaserJet 4(L) and compatibles.

Version 1.04
June 19, 1995

Copyright © 1995 Oliver Hitz

License

Disclaimer

Copyright And Distribution

Package Contents

General

Introduction

Features

Requirements

Compatibility

Installation

The Printer Driver

Installation

Using The Printer Driver

The Preferences Editor

Installation

Getting Started

Using The Preferences

Hints

Known Problems

Troubleshooting

Registration

Updates

Feedback

How To Contact The Author

History

Future

1.2 Disclaimer

Disclaimer

This software is provided "as is". No warranties are made, either expressed or implied, with respect to the reliability, quality, performance, or operation of this software. The use of this program is at your own risk. The author assumes no responsibility or liability for any damage or losses resulting from the use of this software.

1.3 Copyright And Distribution

Copyright And Distribution

The LJ4Boost package including all accompanying files is Copyright © 1995 by Oliver Hitz. All rights reserved.

This software is SHAREWARE. Using it means paying for it. If you use it, please

register

.

This software is freely distributable as long as all files of the original distribution are included without any modifications. The keyfiles registered users get may NOT be distributed. They are NOT part of this package. Distribution of keyfiles is a violation of copyright laws and will be

prosecuted.

This software may not be included into any kind of software collection apart from the AmiNet, the Amiga Library and BBS file areas without written permission from the author.

The autor reserves the right to interdict distribution at any time if the distributor fails to obey to this license agreement.

1.4 Package Contents

Package Contents

This version of the LJ4Boost package consists of the following files:

Directory LJ4Boost/	
LJ4Boost-Install	Installation script V1.02
LJ4Boost-Register	Registration program V1.02
LJ4Boost.guide	AmigaGuide documentation V1.03
Directory LJ4Boost/Devs/Printers/	
LJ4Boost	Printer driver V1.02
Directory LJ4Boost/Locale/Catalogs/	
deutsch/lj4boostprefs.catalog	German catalog for prefs editor V1.02
français/lj4boostprefs.catalog	French catalog for prefs editor V1.0
Directory LJ4Boost/Prefs/	
LJ4Boost	Preferences Editor V1.03

1.5 Introduction

Introduction

The LaserJet4L from Hewlett-Packard® is a very great low-cost laser printer with many possibilities. But one thing is missing for all people that want to use it with an Amiga: A printer driver.

This package is an attempt to provide a printer driver package such as the HP-Explorer, that is shipped along with the LaserJet4L. It covers a standard printer driver especially designed for HP LaserJet 4L and a preferences editor, where printer specific settings can be made.

This printer driver is especially designed for HP LaserJet 4L printers, but as all printers of the HP LaserJet 4 family support the PCL5 printer language, it is very likely that this driver also works on other than the HP LaserJet 4L.

1.6 Features

Features

This printer driver package offers a large palette of features:

- > highly optimized assembler-written Amiga printer driver
- > shorter than any other printer driver (< 4000 bytes!!!)
- > support of ANSI symbol sets
- > support of HP-GL/2 graphics
- > highly optimized compression routines for shorter graphics output
- > automatic/manual paperfeed switch
- > EconoMode switch
- > documentation in AmigaGuide format
- > style-guide compliant, font-sensitive and localized prefs editor
- > style-guide compliant registration program
- > MagicWB style icons (optional)

1.7 Requirements

Requirements

Besides an Amiga Computer with at least OS 2.0 you will need a HP LaserJet 4L compatible printer.

1.8 Compatibility

Compatibility

The HP LaserJet 4L works like all printers of the LaserJet 4 family with the PCL5 printer's language. Although this printer driver was especially designed and tested on a LaserJet4L, it is very likely, that it will also work on other printers of the same family. If you encounter problems or if you discover things that could be implemented for printers other than the 4L, contact the

author

.

In the graphics mode, density 7 is 600 dpi. This setting has been added to allow owners of laser printers other than the HP LaserJet 4L to test this driver on their printers.

1.9 Installation

Installation

The installation of this printer driver package is fully automatically using Commodore's installer program.

If you have installed MagicWB\$^1\$ on your system, you can choose MagicWB icons

during the installation.

After the installation, start the Printer-Preferences and select LJ4Boost to activate it...

^1\$ MagicWB is Copyright © 1992-1994 by Martin Huttenloher

1.10 Installation Of The Printer Driver

Installation Of The Printer Driver

The printer driver is copied into the DEVS:Printers/ directory by the installation program. To activate it, load the Printer-Prefs and select the LJ4Boost printer driver. For more information on the Printer-Prefs, refer to your Workbench manual.

1.11 Using The Printer Driver

Using The Printer Driver

There is not much to say about using the printer driver. In general, you won't have much to do directly with the printer driver. It is used automatically when you tell your programs to print something.

The printer driver uses the "ISO 8859/1 Latin 1" built-in symbol set, when in Amiga (normal) mode. This makes it a lot shorter, because there is no need to include a table with character replacements.

In

ANSI

mode, the printer driver uses the "PC-8 Code Page 437" symbol set ↔

Graphics Printing

The density settings for graphics printings are as follows:

Density Number	1	2	3	4	5	6	7
Graphics Density	75dpi	100dpi	150dpi	300dpi	300dpi	300dpi	600dpi

The 600dpi setting (7) is not supported by the HP LaserJet 4L printer, but I added it here so that owners of other LaserJet 4 printers may also use this printer driver. (Or at least try to use it...)

When selected in the preferences editor, the printer driver tries to reduce the amount of data to transfer by compressing it. This may result in speed improvements. (

Compression And Speed
)

Escape Sequences

For a detailed explanation of the escape sequences supported by this printer driver, see

Escape Sequences

Page Sizes

The AmigaDOS supports various pagesizes in its preferences that cannot be handled on the HPLaserJet 4L. But the HPLaserJet4L also offers page sizes that are not supported by AmigaDOS. The page size settings are as follows:

AmigaDOS	LJ4Boost	Dimensions	Printable Area
US_LETTER	Letter	8.5" x 11"	8.2" x 10.7"
US_LEGAL	Legal	8.5" x 14"	8.2" x 13.7"
N_TRACTOR	DIN A4	210mm x 297mm	201mm x 288mm
W_TRACTOR	DIN A4	210mm x 297mm	201mm x 288mm
CUSTOM	<margins set in the preferences>		
EURO_A0	Executive	7.25" x 10.5"	6.9" x 10.1"
EURO_A1	Monarch	3.87" x 7.5"	3.5" x 7.2"
EURO_A2	COM 10 Env.	4.12" x 9.5"	3.8" x 9.2"
EURO_A3	Intl. DL Env.	110mm x 220mm	101mm x 202mm
EURO_A4	DIN A4	210mm x 297mm	201mm x 288mm
EURO_A5	DIN A5	148mm x 210mm	140mm x 201mm
EURO_A6	DIN A6	105mm x 148mm	96mm x 140mm
EURO_A7	Intl. B5 Env.	176mm x 250mm	168mm x 242mm
EURO_A8	DIN A4	210mm x 297mm	201mm x 288mm

1.12 Escape Sequences

aRIS	ESCc Printer reset
aRIN	ESC#1 Printer reset, set settings from LJ4Boost-Prefs, set AMIGA symbol set, Courier typeface, line spacing and margins (as set in the prefs)
aIND	ESCD LF (without CR)
aNEL	ESCE LF and CR
aRI	ESCM Reverse LF and CR
aSGR0	ESC[0m Underline off, italic off, bold off
aSGR3	ESC[3m Italics on

aSGR23	ESC[23m Italics off
aSGR4	ESC[4m Underline on (floating)
aSGR24	ESC[24m Underline off
aSGR1	ESC[1m Boldface on
aSGR22	ESC[22m Boldface off
aSFC	ESC[nm (30<=n<40)
aSBC	ESC[nm (40<=n<50) no effect
aSHORP0	ESC[0w PICA (10 cpi)
aSHORP2	ESC[2w ELITE (12 cpi)
aSHORP1	ESC[1w PICA (10 cpi)
aSHORP4	ESC[4w FINE (16 cpi)
aSHORP3	ESC[3w PICA (10 cpi)
aSHORP6	ESC[6w 8 cpi
aSHORP5	ESC[5w 10 cpi
aDEN6	ESC[6"z
aDEN5	ESC[5"z
aDEN4	ESC[4"z
aDEN3	ESC[3"z
aDEN2	ESC[2"z
aDEN1	ESC[1"z no effect
aSUS2	ESC[2v
aSUS1	ESC[1v
aSUS4	ESC[4v
aSUS3	ESC[2v
aSUS0	ESC[0v no effect
aPLU	ESCL

	Half LF reverse (with CR)
aPLD	ESCK Half LF (with CR)
aFNT0	ESC(B Courier typeface
aFNT1	ESC(R Letter Gothic typeface
aFNT2	ESC(K
aFNT3	ESC(A
aFNT4	ESC(E
aFNT5	ESC(H
aFNT6	ESC(Y
aFNT7	ESC(Z
aFNT8	ESC(J
aFNT9	ESC(6
aFNT10	ESC(C no effect
aPROP2	ESC[2p
aPROP1	ESC[1p
aPROP0	ESC[0p
aTSS	ESC[n E no effect
aJFY5	ESC[5 F
aJFY7	ESC[7 F
aJFY6	ESC[6 F
aJFY0	ESC[0 F
aJFY2	ESC[2 F
aJFY3	ESC[3 F no effect
aVERP0	ESC[0z 8 lpi
aVERP1	ESC[1z 6 lpi
aSLPP	ESC[nt Set form length n
aPERF	ESC[nq
aPERF0	ESC[0q no effect
aIMS	ESC#9
aRMS	ESC#0
aTMS	ESC#8
aBMS	ESC#2 no effect
aSTBM	ESC[n1,n2r Set top and bottom margins

```

aSLRM          ESC[n1,n2s
                Set left and right margins

aCAM           ESC#3
                Clear margins (set as set in the preferences)

aHTS           ESC#H
aVTS           ESC#J
aTBC0          ESC[0g
aTBC3          ESC[3g
aTBC1          ESC[1g
aTBC4          ESC[4g
aTBCALL        ESC#4
aTBSALL        ESC#5
                no effect

aEXTEND        ESC[n"x
                Extended commands
n:  1 Load ENV:LJ4Boost.prefs
      (NOT set it - to set it, use aRIN command!)
      2 AMIGA symbol set (ISO 8859/1 Latin 1)
      3
ANSI
  symbol set (PC-8 Code Page 437)
  10 Enter
HP-GL/2
  mode
  11 Enter Normal (PCL) mode

aRAW           ESC[n"r
                Next n characters are RAW (e.g. for sending ESC sequences)

```

1.13 ANSI Mode

ANSI Mode

This printer driver also supports printing of ANSI characters. The ANSI mode is invoked by sending ESC[3"x to the printer driver. If you for example want to print a text from an MSDOS machine, simply put this sequence in front of your text and send it to PRT:.. (The only thing you have to pay attention is the line termination. In the current version, this printer driver adds a CR to each LF.)

When in ANSI mode, all characters are printable (except 0, 7-15, 27). To quit the it and to return to the normal AMIGA mode, send ESC[2"x.

By default, the printer driver is in AMIGA mode when the printer.device is opened.

NOTE: When printing color ANSI texts, you may notice that some parts are printed bold. That's because ANSI offers 16 colors, but with escape sequences there are only 10 colors possible. So the bold flag is taken as additional bit for the color number. (By the way: It is not possible to

print patterns for the different colors in the current version.)

1.14 HP/GL-2 Mode

The HP-GL/2 Mode

This printer driver supports the powerful HP-GL/2 (HP-Graphics Language) mode of the printer. If you send ESC[10"x, the printer will be in HP-GL/2 mode until ESC[11"x.

HP-GL/2 is a graphics language mainly designed for plotters. In HP-GL/2 mode graphics are no longer printed as raster images. Instead of drawing a whole picture in the memory of the computer and then sending this as a raster image, it is possible to tell the printer to draw the picture in its memory. Of course this doesn't work for pictures such as scanned photographs, but for other graphics, such as output of CAD programs, it will result in GREAT speed improvements.

If you have programs that offer HP-GL/2 output, simply tell it to print its output to a file and then insert ESC[10"x at the beginning and ESC[11"x at the end and send it to PRT:.

Maybe in

future

versions of this package there will be a custom-designable DOS-Handler that allows to switch into HP-GL/2 mode when e.g. printing a document to PLT:...

NOTE: When switching to HP-GL/2 mode and back, the cursor position is NOT changed.

1.15 Installation Of The Preferences Editor

Installing The Preferences Editor

The preferences editor is installed automatically with the installation script. It is copied to the SYS:Prefs-directory, where all the other preference editors are located.

1.16 Getting Started

Getting Started

The preferences editor may be started either from Shell or from Workbench by double clickin' on its icon.

It is localized, font-sensitive and exactly designed like the standard Workbench preference editors.

Workbench Startup

Supported tooltypes:

```
ACTION=(
    EDIT
    |
    USE
    |
    SAVE
    )
CREATEICONS=(
    YES
    |
    NO
    )

PUBSCREEN
=<public screen name>
```

Shell Startup

The template for starting it from the Shell looks as follows:

```
FROM
,
EDIT/S
,
USE/S
,
SAVE/S
,
PUBSCREEN/K
```

1.17 FROM

Specifies that an saved settings file will be loaded into the editor. This file has to be generated by the menu item "Save As".

1.18 CREATEICONS YES

Specifies that an icon is saved when the configuration is saved. Default is OFF.

1.19 CREATEICONS NO

Specifies that no icon is saved when the configuration is saved. This is the default setting.

1.20 EDIT/S

Specifies that you want to open the editor window to edit a setting. This is the default setting.

1.21 USE/S

Loads in a configuration file and saves it as current setting. The editor window isn't opened.

1.22 SAVE/S

Loads a configuration file and saves it as default setting. The editor window isn't opened.

1.23 PUBSCREEN/K

This option lets you specify the screen the editor window opens on. Default is "Workbench".

1.24 Using The Preferences Editor

Using The Preferences Editor

The preference editor has been programmed according to the style-guide. It works exactly like any other Workbench preference editor, so it is very easy to handle.

Explanation of the buttons

Copies

Paperfeed

EconoMode

Auto Continue

Density

Image Adapt

Page Protect

REt

Compression

Save

Use

Cancel

Explanation of the menus

Project

Open...

Save As...

About

Quit

Presets

Reset To Defaults

Last Saved

Restore

Settings

Create Icons?

NOTE: The printer driver loads the configuration file every time the

printer.device is opened, but the settings are only set if the driver receives the

aRIN command

. This is done always when the printer driver is loaded into memory (the first time you print). After that the printer driver remains in memory and the settings are only set if a program that wants to print sends an aRIN command. (See also

Troubleshooting

)

1.25 Copies

Here you can enter how many copies you want to print. This doesn't mean that the data has to pass multiple times from the computer into the printer, all it does is to tell the printer how many pages he should print.

1.26 Paper Feed

Automatic selects automatic paper feed, Manual selects manual paper feed. If you choose manual feed, the printer's data-led will blink requesting you for paper.

1.27 Econo Mode

This is a special feature of the HP LaserJet 4L. Selecting this will force the printer to reduce the used toner by 50%. This is a very useful switch if you don't need BLACK and SHARP images, e.g. for testing a printer driver... (The costs per page are also reduced by 50%)

1.28 Auto Continue

This option forces the printer to continue automatically after errors have occurred. If "Auto Continue" is disabled, the printer will wait for you to press the button before he continues.

1.29 Density

This lets you change the density settings. "1" is light (uses less toner) and "5" is dark (uses big amounts of toner). This option is useful when printing on folios, as sometimes they need to be very DARK.

1.30 Image Adapt

This option controls the printer's internal data compression mechanism. With 1MB of printer memory, you aren't able to hold one whole page in memory. With this switch set to "On", all data is compressed in the printer to fit into it's memory. The disadvantage of this is, that you loose details. That means, that the output won't look exactly like the input. (It will be less sharp.)

1.31 Page Protect

When printing very dense or complex images, the printer may be too slow to handle input and output at the same time. If you select "On", the printer will first save the whole page in it's memory before printing it. Choose "Auto" if you only have 1MB of printer memory, as you won't be able to hold a whole page in memory. Choosing "Off" gives you the best performance, but there can be errors from time to time, dependent from the complexity of your output.

1.32 REt

Resolution Enhancement technology (REt) is a feature that enhances the resolution of your printer. This is done by refining pixels with smaller pixels. To gain optimal quality, use this option together with Density.

1.33 Compression

This controls which compression methods will be used for graphics printing. ←

"None" disables all compression, "Run-Length" enables run-length compression, a very simple algorithm. "TIFF" selects an algorithm similar to the one used when encoding IFF ILBM pictures, and "Run-Length & TIFF" selects both of them, where each line is compressed with both methods and the shorter one is sent to the printer.

For more about compression :
Hints

Compression And Speed

1.34 Save

This button saves the current settings as your default setting and quits the editor.

1.35 Use

This button saves the current setting as your actual setting that remains active until you reset your computer. It quits the editor.

1.36 Cancel

This button quits the editor without changing anything in the active settings.

1.37 Open...

This menu item lets you load a setting that you have saved to disk some time before.

1.38 Save As...

This menu item lets you save a setting to disk. If you have activated the Create Icons? menu, then an icon will be added to your file.

1.39 About

Probably the most important menu point...

1.40 Quit

Quits the editor without changing anything.

1.41 Reset To Defaults

Resets the current settings to the default system settings. These settings cannot be modified.

1.42 Last Saved

This menu item loads in the last saved configuration settings saved with the Save button.

1.43 Restore

Loads the currently active settings.

1.44 Create Icons?

If this menu item is checked, then everytime you save a configuration using the Save menu item, the icon called "ENV:Sys/def_pref.info" is added to the file. Note that NO icon is saved if you just press the Save button.

By default this option is OFF unless you specify the CREATEICONS tootype when starting it from the Workbench.

1.45 Hints

Hints

Compression

The compression modes used by the HP LaserJet 4L are only very simple ones. Together with the compression routines in the printer driver, they can improve the time required to print graphics even on a normal 68000 based system. (

Compression And Speed
)

1.46 Compression And Speed

Compression And Speed

It is difficult to say whether compressing data results in big speed improvements or not. Everything depends on the data. The printer driver always cuts off all 0-bytes to the right of a line. This is done even if there is no compression selected, as this costs almost no time to do and the efforts can be great as often there are half-empty or even empty lines.

1.47 Known Problems

Known Problems

FinalWriter

Some versions of FinalWriter reset the printer a couple of times during a printout. This causes empty papers, especially when the printer driver is loaded into memory. (When it is loaded into memory for the first time, the printer is reset automatically.)

If you should encounter problems, please contact the author with a clear explanation of your problem and a short summary of your equipment. (Not because I'm curious, but because the problem could be caused by your equipment)

1.48 Troubleshooting

Troubleshooting

The settings from the LJ4Boost-Prefs have no effect.

The settings from the prefs are only set when the printer driver is loaded

into memory or when the driver receives an
aRIN command

.

This has been made because when the the settings is set all pages still in memory would be printed out, and sometimes this could cause problems e.g. when a program closes and re-opens the printer.device during one page (the contents of the page would be scattered over multiple pages).

This command can be sent manually using the "InitPrinter" program found on the Workbench disk, or from CLI via the following line: 1.> echo >PRT: "*E#1" noline

1.49 Registration

Registration

This printer driver package is SHAREWARE. This means you HAVE to pay for it if you use it.

The registration fee is SFr 20, DM 20 or US\$ 20 (The US\$ is very low at the moment...). No other currencies are accepted. Do only send cash. Otherwise there is no guarantee that you will receive an answer.

If you register, you will receive a labeled disk with the latest version of the "LJ4Boost Printer Driver Package", along with a personal keyfile that allows you to use future versions of this program. For more information on where and how to get updates, see

Updates

.

Please do ONLY register with the registration utility provided in the original distribution. (Let's hope it works on all Amigas...)

[Click here to start the registration utility NOW](#)

Please allow 2-4 weeks for delivery, depending on where you live.

1.50 Updates

Updates

It is not shure wheter there will be any updates of this package or not. The more registrations, the more likely it is that there will be any updates. Anyway, if there should be any updates, they will be available in the AmiNet and on the

FriByte BBS

.

For possible future features, see

Future
.

1.51 FriByte BBS located in Fribourg/Switzerland

```

* ----- *
*
* / \ / \
* \^^^\ ##### \^^^\ ##### ## ##### ##### *
* (@ @) ##### ## ##### ## ##### *
* / \ ##### ##### ## ## ##### ##### *
* \\textdegree{} \textdegree{}/ ##### ## ## ##### ## ## ## ←
* ##### *
* ~ ##### ## ## ##### ## ## ##### *
*
* ----- PCBoard V15.21 *
*
* CALL: +41 - 37 - 432 540 (24h - ZyXEL 19k2) *
*
* AMIGA * MSDOS * HP48 ----- RomandNetwork Host *

```

If you don't want to register on this BBS, just login as »USC« with no password. You will then be allowed to download the latest version of LJ4Boost and to write a message to the autor.

1.52 Feedback

Feedback

The author is very pleased about bugreports, ideas or anything else apart from letter-bombs...:-(Feel free to write the author what do you think about this package.

For the address, see

How To Reach The Author
.

1.53 How To Reach The Author

How To Reach The Author

E-mail: Oliver.Hitz@unifr.ch

Snail-mail: Oliver Hitz
Weiermattweg 13
3186 Düringen

Switzerland

...or simply call:

```
FriByte BBS
and leave a message for Oliver Hitz.
```

```
- - - - ----* Up The Irons! *---- - - - -
```

So it shall be written - so it shall be done.

1.54 History

- V1.04 (19.06.95)
 - LJ4Boost V1.02
 - fixed a bug concerning the margins (Thanx to Dirk Vael)
 - LJ4Boost-Register V1.02
 - fixed minor bug

- V1.03 (10.05.95)
 - added MagicWB style icons (optional) (Thanx to Martin Huttenloher for his permission)
 - LJ4Boost V1.01
 - better detection of FormFeeds (-> less blank pages...)
 - LJ4Boost-Prefs V1.03
 - caused Enforcer hits when requester was displayed and the window was not opened yet (Thanx to Paul van der Heu)
 - used a function only available under OS3.0 and higher (Thanx to Rene Amador)
 - LJ4Boost-Register V1.01
 - fixed bug! (Thanx to Rene Amador)

- V1.02 (16.04.95)
 - LJ4Boost-Prefs V1.02
 - crashed when locale.library could not be opened (Thanx to Alexander Schwenk)
 - added french catalog

- V1.01 (11.04.95)
 - LJ4Boost-Prefs V1.01
 - fixed bug in the tooltypes (didn't work properly)
 - fixed Enforcer hit

- V1.0 (06.04.95)
 - first public release

1.55 Future

Future

If there will be some future versions of this printer driver package, then the following features will probably be added:

- add features from HPLaserJet4L compatible printers (with YOUR help!)
- make use of the read-back possibility of the HPLaserJet4(L)
(I'd be very glad if anybody could tell me how to do this :-)
- delta-compression for graphics
- 68020+ optimized version
- foreground-/background-color patterns (great for ANSIs!)
- customizable DOS-Handler (to create ANSI: or PLT:...)
- multi-lingual documentation + registration utility
- more catalogs
- selectable code tables

...and many more. You can be sure of it!
