

**FDA**

<b>COLLABORATORS</b>
----------------------

	<i>TITLE :</i> FDA	
<i>ACTION</i>	<i>NAME</i>	<i>DATE</i>
WRITTEN BY		August 24, 2022
		<i>SIGNATURE</i>

<b>REVISION HISTORY</b>
-------------------------

NUMBER	DATE	DESCRIPTION	NAME

# Contents

<b>1</b>	<b>FDA</b>	<b>1</b>
1.1	FDA	1
1.2	FDA/Concepts	2
1.3	FDA/Requirements	4
1.4	FDA/Benchmarks	4
1.5	FDA/Tested Systems	5
1.6	FDA/Registration	8
1.7	FDA/Free Email	10
1.8	FDA/Free FAX	10
1.9	FDA/Installation	10
1.10	FDA/Preferences	11
1.11	FDA/MainWindow	12
1.12	FDA/DeviceWindow	14
1.13	FDA/InfoWindow	16
1.14	FDA/View	17
1.15	FDA/Copyright	19
1.16	FDA/Author	21
1.17	FDA/Features	22
1.18	FDA/FileSystem installation	24
1.19	FDA/DataSafety	25
1.20	FDA/Future	26
1.21	FDA/History	26
1.22	FDA/Other Products	30
1.23	FDA/Credits	32
1.24	FDA/Speed up	35
1.25	FDA/SCSIdevice installation	36
1.26	FDA/TurboBoards	37
1.27	FDA/Mark Bad Memory	37
1.28	FDA/OS more reliable	38
1.29	FDA/Known Bugs	38

---

1.30 FDA/New Bug . . . . .	41
1.31 FDA/DebugFiles . . . . .	42
1.32 FDA/Technical . . . . .	43
1.33 FDA/Programmers . . . . .	45
1.34 FDA/Default . . . . .	46
1.35 FDA/ReturnNumbers . . . . .	46
1.36 FDA/Index . . . . .	47

---

# Chapter 1

## FDA

### 1.1 FDA

Future Drive Accelerator V1.4 documentation and newer

\*\*\*\*\*

Uses the free memory as a cache , the program reacts automatically on changes in memory resources, so that you will always get the maximum speed for your drives. Even "resources-hungry" programs will get enough memory.

Introduction:

Concepts

The concepts behind Future Drive Accelerator

Requirements

What you need to use Future Drive Accelerator

Benchmarks

What speed improvements can be achieved with Future Drive Accelerator? ↔

Tested Systems

Tested computers

Registration

If you like the demo...

Usage:

Installation

How to install and run Future Drive Accelerator

Preferences

How to configure Future Drive Accelerator

View

How to quit and monitor Future Drive Accelerator

Important informations:

Copyright  
Copyright and other legal stuff

Author  
Where to send bug reports, comments and orders?

About the program and the author:

Features  
Compatibility and features of Future Drive Accelerator

Future  
Whats more?

History  
Development history of Future Drive Accelerator

Other Products  
Other products

Credits  
The author wishes to thank...

For curious people:

Speed up  
How to make Future Drive Accelerator even faster

Mark Bad Memory  
How to use faulty memory without problems

OS more reliable  
How to make the Amiga more reliable

Known Bugs  
Known/new bugs

Technical  
Specifications, data security, 4 GigaByte hard disks, ATA[PI]...

Index  
Index for this document

## 1.2 FDA/Concepts

---

The concepts behind Future Drive Accelerator

\*\*\*\*\*

Future Drive Accelerator is a disk-cache program.

A cache buffers all data which is written or read from the drive (hard disks, floppy disks, Compact-Disk, removable disk, ZIP...).

If requested data is already in the cache, it doesn't need to be loaded from the slow disk.

So far nothing new!

Memory is, as we all know, always short. So you better think twice before you give it to programs. No matter how you set it up, you can never make it suitable for all programs. One program runs (thanks to the cache) faster than ever before, another one stops working (due to the lack of RAM).

With all other cache programs, you had to adjust the memory usage. Of course, the more memory a cache can use, the faster it will work. So with old cache programs the memory usage had been set quite high, but because other programs stopped working this was stopped rather quickly. Now the cache is commonly set to an average size, so that all "memory-eating" programs run. Or you always had to change the cache-size manually to fit the current situation. But this is not a very satisfactory solution. And this is where Future Drive Accelerator comes in.

The whole free memory, whose size is changing all the time, is used as cache.

With this technique, an Amiga with a 68030 50Mhz processor and 16 MByte FastMemory (Blizzard IV) averages a factor 4 speed up. See  
Benchmarks

.

Write accesses are buffered, and later, while writing back to the drive, the head is moved from the highest to the lowest address.

Another improvement is built-in for people who use exchangeable media like disks, CDs, MagnetOptical-disks and ZIPs. When inserting the media again, the still filled cache is used. The media doesn't need to be accessed again.

Who used a lot of dos-buffers? (1) for the file system, you can now even save this memory.

Not to mention that you help protecting the environment. The motor and the electronics of the drive is used less and thus, energy is saved.  
=> the nuclear power plants can be shutted down earlier.  
You should also keep in mind that the hardware wears out less.

----- Footnotes -----

(1) A dos-buffer requires (per default) a half KiloByte.

## 1.3 FDA/Requirements

What is required to use Future Drive Accelerator?

\*\*\*\*\*

Future Drive Accelerator needs at least:

AmigaOS 2.0  
or better.

2 Megabyte memory, more memory is recommended.  
Additionally, the following software is supported:

DiskSafe (<http://de.aminet.net/pub/aminet/disk/salv/DiskSafe.lha>)  
After a reset or system crash, the cache will be written back before  
restarting the system.

Example installation for s:Startup-Sequence:

```
DiskSafe DF1: DF0: HD0: Store: Font: HD2: HD3: HD4: ... REBOOT QUICKKEY ←
WAITVERIFY VERIFYREQ LOGFILE=Store:T/DiskSafe.log IGNORE
```

If this shouldn't work, try adding RESETKEY.

CopyMemQuicker  
See

Speed up  
.

FileSystems, Devices  
See

Features  
.

## 1.4 FDA/Benchmarks

What speed improvements can be achieved with Future Drive Accelerator?

\*\*\*\*\*

- \* Copies 850KB in 35 seconds from hard to floppy disk, this equals the speed of formatting. This is possible because, minimizes the overall seek time required to read or write data from or to disk. Outstanding I/O requests are ordered such that they can all be performed "with one sweep" of the disk head assembly, from the highest to the lowest disk address (Elevator seeking).
- \* 23 MB/s while reading, (SysInfo V3.23) instead of 7 MB/s without cache, with an Amiga and following equipment: Zorro III, CyberStorm MKIII, 060/PPC 604 150Mhz, UltraWide SCSI HD, 64 MB FastMemory, CopyMemQuick 40+.
- \* The booting can get twice as fast if there are a lot of small files to load and many files reside in the WBStartup directory.
- \* Faster access to directories from Workbench.



- \* Amiga MC68030 50MHz, 16MB FastMemory.
- IDE-HardDisk (tested with DiskSpeed) (1)
    - read 6.8 times faster.
    - write 8.1 times faster.
  - DD-FloppyDisk (tested with DiskSpeed)
    - read 488.0 times faster.
    - write 997.6 times faster.
  - Copying from one partition to another.
    - 44 Dirs, 561 Files = 2.3MB Size
    - c:Copy MUI: ASWAP:MUI ALL CLONE QUIET
    - Dos 457 Dos-Buffers 46 secs 253999 micros
    - FDA 7 Dos-Buffers 11 secs 196642 micros (4.13 times faster)
- \* Amiga PPC604 233MHz MC68060 50MHz, 96MB FastMemory.

- IDE-HardDisk (tested with DiskSpeed)
  - read 19.5 times faster.
  - write 20.4 times faster.
- SCSI-HardDisk (tested with DiskSpeed)
  - read 3.8 times faster.
  - write 3.5 times faster.

(FDA-Benchmarks.guide)Main More (graphical) statistics, which have been ←  
created using DiskSpeed.

----- Footnotes -----

(1) DiskSpeed Reference: 262144 byte, MEMF\_FAST, LONG-aligned buffer.

## 1.5 FDA/Tested Systems

Tested systems

\*\*\*\*\*

Hardware List

A4000/40/40Mhz PPC 200Mhz + 64 Fast  
CVPPC + 8Mb  
Zip Drive  
Oktagon Controller  
1.3Gb SCSI II Hard Drive (1 partition)  
4.3GB SCSI III Hard Drive (3 partitions)  
Toshiba 12xCD  
IOBlix Super Fast Serial Card  
Epson GT-6000 Flatbed Scanner  
Pace 56 Voice (V90) (ISP=Wirenet)  
Micronik A4000 Tower case

Epson Stylus Color 800  
External floppy Drive  
Minolta 7000 Camera  
External Speakers  
MicroVitec GPM 1701 Monitor  
Tabby (Drawing Pad)  
Sound Sampler  
Prelude Sound Card

#### Software Most Often Used

AHI (music to your ears - registered)  
All Experimental PPC Software  
PFS2 (So so fast)  
CybergraphX V4 (Good with CVPPC)  
PPaint 7.1 (It's all in the eye of the beholder)  
ImageFX Ver 3.2 (Very stable at this upgrade)  
Netconnect (Kiss - Keep It Simple Stupid)  
Miami (Works great with my IOBlix)  
Turboprint 6.02 (Faster now as it's using the PPC Module)  
PageStream 3.3a (I love it)  
Organiser (Who am I)  
Opus Magellan II (My god, it's full of stars)  
CandyFactoryPro (Good PPC Program)  
Zip Drivers (Backup my Backups)  
HappyDT (Sometimes crashes Netconnect and other programs)  
Elastic Dreams (Game for a laugh)  
Cyberview (Registered)  
Cybershow (Registered)  
AK-Datatypes (Registered)  
Quicksampler (Good PD)  
MultiCX (Registered)  
OxyPatcher (Make Those Programs Burn)  
MUI (3.8) (Workbench 4 perhaps?)  
Kingcon (No two shells are the same)

#### Relaxing Software Used

Genetic Species  
Foundation  
Alternate Reality (RPG)  
Bane of the Cosmic Forge (RPG)  
Bards Tale (RPG)  
Quake  
UFO  
Dungeon Master 1 & 2 (RPG)  
Ultima VI (RPG)  
Birds of Prey  
Theme Park  
Civilisation  
Syndicate  
Doom  
Stratego (PD)  
Myst  
Colonization  
Frontier Elite II  
Deluxe Galaga

---

Shadow Of The First Moon  
 VChess  
 JetPilot  
 Tiny Troops  
 Blade (Good Iso RPG)  
 EaglePlayer (Registered)  
 MrJQuote

Amiga 1200:

+ 2 880KB Floppys  
 + 2 MegaByte 32 Bit Fast-Memory  
 + Turbo Jet A1230-BOARD @ Harms Computertechnik  
 MC 68030+MMU 14.2 MHz Cache Burst VBR=\$0  
 FPU68881 15.4 MHz  
 + WesternDigital Caviar 2850 (850MB)  
 - since I have this HD, I had to slow down my MC68030 from 28MHz to  
 14.2 MHz. If anybody knows a solution, I would really like to know.  
 See  
 Autor  
 .

CPU :MC 680030 50MHz  
 Computer :Amiga 1200  
 OS :V 3.0  
 Controller :IDE (Buddha)  
 Memory :16MB FastMem  
 2MB Chip  
 FileSystem :FastFileSystem 44.5  
 Hard Disk :1x Quantum Fireball 3.68 GB  
 ZORRO-II-Karten :1x MultifaceIII, 1x Buddha IDE  
 other cards :Blizzard 1230 (CPU-PORT)  
 others :Micronik Tower mit Zorro II Datherborad  
 running programs :Prometheus V2.6, FKey, MouseBlanker, MultiCX V2.78,  
 NewIcons V40.2, PowerIcons V1.0, SleepingPointers  
 V1.0a, Multifax Spooler V3.1, Killclick2

CS PPC 233MHz, 060 50MHz

A4000 MC68040 25MHz 16FastMem

A3000 CSPPS 604/200 060/50

PicassoII running cybergraphics (will soon be CVPPC)  
 4 different SCSI harddisks of which 3 are SCSI-2 and one UWSCSI  
 CSPPC-interface.  
 DAT-tapestreamer, CD-ROM, 70MB RAM and many things I can't remember.

Amiga 4000 with 68040/40Mhz, about 80MB Fastram, most of it  
 on the turboboard, and 3,5MB Fast on the motherboard.  
 2nd.scsi.device / scsi.device / ffs/afs/sfs..

Amiga 1200 040/40 2/32MB 2GB TowerhawkII X2 Multiscan

CPU : MC 68040 40MHz  
OS : V 3.1  
Controller : IDE  
Memory : 32MB Fast, 2MB Chip  
FileSystem : FastFileSystem 43.19  
Hard disk : 1 2GB-Platte with 2 Partitionen (50MB and the rest)  
CD : 1 4fach-CD-Rom (RandyCD-Rom)  
DirOpus5 Magellan is used as Workbench replacement.

## 1.6 FDA/Registration

If you like the demo...

\*\*\*\*\*

If you like this demo-version you might want to use the full version which features:

- \* Faster, because the complete free memory is used as cache.
- \* Unlimited number of cached drives.
- \* And of course no time limit.

Ordering the full version is easy, convenient and comfortable - 24h a day worldwide!

### Prices

- \* The full version is available for only 19,99 DM (\$12.99) (11,99 EUR).
- \* Minus 5,- DM (-\$3) (-2,60 EUR) if PowerCache, DynamiCache or HyperCache can be leased.
- \* Minus 4,- DM (-\$2.5) (-2,10 EUR) if you are a student, unemployed or a pensioner ;-). Please add some proof. See  
Author  
.
- \* Plus 4,- DM (\$2.5) (2,10 EUR) (outside Europe 8,- DM (\$5) (4,20 EUR)) shipping, if you can not receive Email. See  
Free Email  
. For an update,  
just transfer the money to my bank account.
- \* Update 0,- DM (\$0) (0 EUR) if it can be sent via Email. See  
Free Email  
.
- \* Special prices for 10 or more users. Prepaying of licenses and commercial reselling is also possible. Please contact the author for more details.  
See  
Autor  
.

## Ordering

1. Online in the World Wide Web (<http://shareit1.element-5.de/programs.html?nr=102792>), SSL encoded. ↔

## \* Credit cards

- Visa
- Eurocard/Mastercard
- American Express
- Diners Club

## \* Wire-transfer

2. per Phone, FAX or E-Mail

## \* ShareIt service.

(Program-number 102792)

-

## FAX

- : +49-221-2407278 (Germany)
- Phone: +49-221-2407279 (Germany)
- FAX: +1-724-8508187 (USA)
- Phone: +1-800-9034152 (USA) free
- Phone: +1-724-8508186 (USA)
- E-Mail: <MartinTauchmann@bigfoot.com>

3. US check

Send \$15.5 to the address below, include the program-number 102792.

ShareIt! Inc.  
PO Box 844  
Greensburg, PA 15601-0844  
USA

4. Eurocheque

Please fill in the amount in EUR and send to the author

.

5. Bank transfer

Transfer the money in EUR or DM to:  
Badische Beamtenbank eG (Germany)  
76119 Karlsruhe  
Bank Location Number: 660 908 00  
Martin Tauchmann  
Account Nr.: 2473135  
Usage: FDA MC68020 <Your E-mail address>

6. Cash (worldwide)

Put the money in an envelope and send it to the Autor

. (Use an envelope where the money can't be seen against the light.)

---

## 1.7 FDA/Free Email

Free Email  
=====

```
`http://mail.yahoo.com'  
`http://mail.angelfire.com'  
`http://www.gmx.de'  
`http://www.dejanews.com' (No problems with a "FireWall")
```

## 1.8 FDA/Free FAX

Free FAX  
=====

```
`http://www-usa.tpc.int/sendfax.html?destnumber=49 221 2407278'
```

## 1.9 FDA/Installation

How to install and configure Future Drive Accelerator

\*\*\*\*\*

Please use the included installer script to install Future Drive Accelerator. The AmigaOS Installer V43.3 is required. This version can be found in Aminet.

Future Drive Accelerator can be started in different ways:

- \* Move it to the WBStartup directory, and remove the brackets from the tooltype QUIET. (Workbench-Menu ->Pictogram ->Information

- \* or insert this line:

```
RUN <>NIL: SYS:System/FDA QUIET in the file S:Startup-Sequence after
```

- SetPatch

- SaferPatches

  - (<http://de.aminet.net/pub/aminet/util/misc/SaferPatches.lha>) or SetMan

- PoolMem See

  - NoRamReverse

  - .

- HDOff (not really necessary, but you can then work with the cache when the harddisk is off.)

Future Drive Accelerator uses the following Workbench Tool Types and Shell

---

parameters:

FROM (Only from Shell)

Specifies the name of the configuration file.

QUIET

Initialising messages are not printed.

This is useful for an installation in the SYS:WbStartup directory, or the S:Startup-Sequence.

## 1.10 FDA/Preferences

How to configure Future Drive Accelerator

\*\*\*\*\*

Future Drive Accelerator can be configured using the Future Drive Accelerator Preference Editor:

MainWindow

The Mainwindow

Windows for configuring drives:

DeviceWindow

The DeviceWindow

Other windows:

InfoWindow

Informations about the drive

The Preference Editor uses the following Workbench Tool Types and Shell parameters:

FROM (Only from Shell)

Specifies the name of a configuration file to load.

EDIT (default option)

The configuration can be changed.

USE

The new configuration will be saved temporary.

SAVE

The new configuration will be saved permanently.

MAINPROGPATH

Directory of Future Drive Accelerator, e.g. Sys:System/. The configuration (FDA.prefs) will be saved to the directory. If Future Drive Accelerator

---

loaded before ENV: is initialized, which is the case when booting from floppy disk, the config will be found anyway.

## 1.11 FDA/MainWindow

The Mainwindow

=====

The MainWindow contains a listing of drives. When you select a window, a new window (see

Device Window  
) will be opened.

```

|$ \times $ | Future Drive Accelerator Preferences | . |
|
| Not used FastMemory      #          70 KB |
|
| Not used ChipMemory      #          50 KB |
|
|                               FastMemory first |
|
| View color flash if track moved or deleted |
|
| Protect tracks in memory with checksummes |
|
||
|
| DF0: trackdisk Unit 0 LowCyl 0
|         enabled... | | | |
|| DF1: trackdisk 1 LowCyl 0          enabled... | | |
|| RAD: ramdrive 0 LowCyl 0          disabled... | | |
|| HD0: scsi 0 LowCyl 23             enabled... | | |
|| HD2: scsi 0 LowCyl 231           enabled... | ^ | |
|| SWAP: scsi 0 LowCyl 558          enabled... | | |
|
| | | | | | |
| |
| Save
| |
| Use
| |
| Cancel
| |
| | | | | | |
|

```

Not used FastMemory  
For calibration.  
How much of your fast memory shall not be used as cache?  
60 kiloBytes is a good value here, because a minimal amount of memory is necessary to send messages. This way, memory can be made available faster.

Not used ChipMemory



For calibration.

How much of your chip memory shall not be used as cache?

100%=No chip memory will be used => which is the fastest setting.

FastMemory first

Off: The cache uses ChipMemory first, then FastMemory.

On: The cache uses FastMemory first, then maybe ChipMemory.

View color flash if track moved or deleted

Off: No color flash is created.

On: There will be a green flash, when a part of the cache is moved in the RAM.

There will be a red flash when a part of the cache is removed from RAM.

Rem.:This option is useful to calibrate Not used Fast- ChipMemory.

Protect tracks in memory with checksummes

Off: The cache is not protected.

On: The cache will be protected from external programs.

Rem.:This is recommended for Intros, games and badly programmed software which change foreign memory blocks. See

Enforcer-write-hits

.

Or if you have bad memory. See

Defekten Speicher

.

Remember: The FileSystem itself calculates checksums. If you get an "Warning!"-Requester with a "checksum-error" , you may not, in no case, press "Cancel", but instead reboot your Amiga at once!

This may also happen without Future Drive Accelerator, but it is not so likely that a program wrote into the dos-buffers accidently.

Dos-buffers just are a "smaller target".

The buttons at the bottom of the window are used to set the path where the config-file will be saved. The name of the file is FDA.prefs.

Save

The configuration is saved to the ENVARC: directory. The new config will be used automatically by Future Drive Accelerator and will survive a reboot. The preferences editor will quit after saving.

Use

The configuration is saved to the ENV: directory. The new config will be used automatically by Future Drive Accelerator but will not survive a reboot. The preferences editor will quit after saving.

Cancel

To quit the preferences editor. All changes will be lost.

Default

What are the default values?

---

## 1.12 FDA/DeviceWindow

The Device Window

=====

The following can be set in the Device Window:

When data is written back to the drive, if the data should be verified, how much data should be pre-read and how much of the cache can be used by this drive.

```
|$\\times$|FDAPref Option for HD0:           |  |
|
|                   Removeable Disk?      |
|                   Verify write          |
|           Write ^| async (fastest) |
| ASync delay (seconds) #                4 |
|
| Size of Track #      <>R 43008 |
|
| Cache usage priority #                0 |
|
| |   |   |   |   |   |   |   |
| |   |   |   |   |   |   |   |
|
|                   Enable
|                   |   |
|                   Info
|                   |   |
|                   Disable
|                   |   | | | | | | |
| |   |   |   |   |   |   |   |
| |   |   |   |   |   |   |   |
```

### Removeable Disk?

Does this drive contain a removable disk?

e.g.: floppy-, CompactDisc-, ZIP, MagnetOptical or SyQuest-drive.

If Removeable Disk is set to Off, then Future Drive Accelerator does not need to know which FileSystem is used, to recognize a disk after re-inserting.

=> The initializing of the cache is faster.

### Verify write

The data will be checked if it has been properly written.

=> Useful for floppy-disk and old hard-disks.

### Write

- Through

Data will be saved at once and moved into the cache at the same time (write-retention).

=> When the data is read again, it can be accessed by the cache very fast.

- Sync  
Like Through with the difference that the data is written to the drive (1) after the writing of the file was completed (2) .  
=> The parallel reading and writing is done more gentle in multitasking.  
=> The program waits for the end of the write-access (Synchron).

- Async  
Like Sync, but the program doesn't wait for the end of the write-access (ASynchron). What means data is written in an instant.  
=> Additionally, minimizes the overall seek time required to read or write data from or to disk. Outstanding I/O requests are ordered such that they can all be performed "with one sweep" of the disk head assembly, from the highest to the lowest disk address (Elevator seeking).

The cache is written in the background.

=> You can write data to the cache, while the cache is writing to the drive.

See

Datasafety

.

- Late as possible  
Like Async but the data is written as late as possible. This is recommended for Cache-directories of World-Wide-Web browsers or Internetcomputer, where there is (more or less) always data written.

Data is written when memory is needed or Future Drive Accelerator exits, and, if DiskSafe is installed, before a Reset/System-crash.

See

Requirements

.

- For temporary  
Like Late as possible but data is NOT written before a Reset/System-crash.  
=> This is useful for directories whose contents don't need to be the same after the reset, for example: env: t:.

Async delay

For how many seconds shall the write-back be delayed with Async?

Size of Track

Number of bytes a track (3) requires in the cache.

=> How many bytes shall be read ahead?

Reommended values are for harddisks and CDs about 40KB and for floppy disks (2 tracks = 1 cylinder).

If the harddisk is not fragmented, you could achieve a dramatic speed improvement when you set a high value.

If you use two or more harddisks you should use the same value for all unit to avoid the fragmenting of memory. This will be improved in future versions.

Cache usage priority

What priority has this drive compared to other drives for caching?

The buttons in the bottom row of the window can be used to activate or deactivate the cache, and to get informations about the drive

Enable

Cache active.

Info

Shows  
                   informations  
                   about the drive.

Disable

Cache inactive.

----- Footnotes -----

(1) Synchron write-back, or the asynchron delay is started when:

- e.Update-command from FileSystem,
- e.Motor-off-command from FileSystem,
- If a program requests memory, and the cache (the whole RAM) is filled with data that has to be written back.
- Disk removed : "You must replace Volume"
- If DiskSafe is installed : Before a Reset or a Guru.
- or if the cache is full with data to write (at least 7 free tracks)

(2) The end of the write-access is signalled explicit by the FileSystem to make sure that a device, software- or hardware-cache in the harddisk has written the data completely.

Most harddisks have an internal cache of 64 KB.

(3) If only a block (part) of the track is read, the hardware copies the whole track into a buffer and passes on only the requested Block. Future Drive Accelerator makes use of this behavior: It always reads the whole track into the cache. Reading of a Tracks is a little bit slower than reading a block. slow hardware-head, which would be necessary for reading another block. => And the hardware isn't stressed because the requested block is already in the cache.

## 1.13 FDA/InfoWindow

                  Informations about the drive

=====

This window shows informations about the selected drive.

Size of Block

can be modified using the HDToolBox(C)AmigaInc. or in the mountfile in the directory Devs:DosDrivers (SectorSize \* SectorsPerBlock). But this is not recommend, because most programs depend on a value of 512 here.

No of Tracks

Number of tracks. Is also the capacity of the partition, floppy ... multiplied with Size of Track.

**First Track Number**

Start positions of the partition on the harddisk.

**Root Track**

Depends on the FileSystem. Is used by Future Drive Accelerator to recognize a floppy/removable disk only.

**Name and Dates Position**

The position where the partition-name, the date of creation and the date of the last modification can be found. Is used by Future Drive Accelerator to recognize a floppy/removable disk only.

**Unit Number**

Hardware Unit Number.

**Device Name.**

Name of the Software-Device.

**Buffer Memory Type**

Either Chip- or Fastmemory. If "Need! ChipMemory (slow)" appears here, you should get more recent Device-Software, or try to set BufMemType=1 in Devs:DosDrivers, because the drive is slower than it needs to be.

**4-GByte ``boundary``**

If anything else than "No problems" appears here, then this partition is beyond the "4 GB boundary"; you should make sure that you use a FileSystem and Software Device that can handle harddisks bigger than 4 GigaByte. See

FileSystem installation

.

**New Style Device**

Supports the Device-Software the new device standard(C)AmigaInc.?

## 1.14 FDA/View

**How to quit and monitor Future Drive Accelerator**

\*\*\*\*\*

Future Drive Accelerator can monitored and exited using  
Future Drive Accelerator View:

The monitor accepts Workbench Tool Types and shell parameters:

**KILL-FDA**

Writes the cache to the drive (if necessary) and quits Future Drive Accelerator.

**FLUSH**

Flushes the cache, except for data that has to be written to disk.

**UPDATE**

Writes the cache to the drive (if necessary).

Future Drive Accelerator View is a by-product, which has helped the author while developing Future Drive Accelerator to find the optimal algorithm (1) for using the cache. The author didn't plan to release this program, but does it now anyway for the curious ones.

Normally, Future Drive Accelerator View is only required to quit Future Drive Accelerator.

The right part of the window shows the current cache structure (sorted). Above this is a summary of the list, how many tracks are in memory and how many of them are waiting to be written to the drive. On the left side you can control how the list should appear. Finally, at the top, you can see how much of the free memory is used as currently as cache (Avail Memory).

A simpler statistic would be of no use, because the cache is always used at 100%.

Sorted by

#### Location

Lists the memory areas where the cache-parts reside (2).

The whole cache is listed.

- Location Start position of the track in memory.
- Type Memory Type
- Size Number of Bytes a tracks uses in the cache.
- Track Number of Track. No. 0 is the first.
- Used Number of accesses to the track.
- Old Time (in seconds) since the last access.
- Parti Logical partition- or drive-name.
- DiskName Virtual partition-, medium- or disk-name.

Above this is written how many tracks are in the cache altogether (all free memory) and how many of that must still be written to the disk.

#### Track

Lists the cache-parts of a partition, medium or disk.

- Track Number of track. No. 0 is the first.
- Location Start position of the track in memory.
- Type Memory typet.
- Used Number of accesses to the track.
- Old Time (in seconds) since the last access.
- Flags
  - \* NowBusy Track is read or written.

\* MustWrite Track must be written.

Above this is written how many tracks of the medium (3) are in the cache and how many of that must be written to drive.

The next lines contain

2. the Unit the medium/partition belongs to, the name of the device and the start position (track-number) of the partition on the disk.
3. logical partition- or drive-name and virtual partition-, medium- or disk-name.
4. When the medium was created (formatted) and the date of the last modification. (Only FastFileSystem)

Page Up

One page up.  
<Cursor left, Shift+Cursor up>.

Page Down

One page down.  
<Cursor right, Shift+Cursor down>.

Top

Top of the list.  
<Key T>.

End

End of the list.  
<Key E>.

Before Medium

Jump to the previous medium.

Next Medium

Jump to the next medium.

----- Footnotes -----

(1) The used algorithm is required to figure out which tracks is the last in the queue. This is the oldest track, and if there are several tracks of the same age, the tracks with the smallest access counter is killed. If you know a more effective algorithm, don't hesitate and let me know.

(2) The cache is a summary of different tracks.

(3) A medium can be a partition, an inserted diskette/ a removable harddisk / CD or a removed diskette...

## 1.15 FDA/Copyright

---

Copyright and other legal stuff

\*\*\*\*\*

Copyright (C) 1998-1999 Martin Tauchmann

This documentation may be copied and spread as long as the copyright note and this copy permission remains unaltered in all copies.

COPYRIGHT

Copyright (C) 1998-1999 Martin Tauchmann

Future Drive Accelerator is shareware. In this case, that means that you need a personalized version of the program to use the full functionality of Future Drive Accelerator.

Users get a personalized version when they have registered with me. This personalized version may not be given to anyone else. To give away the personalized version or to use versions of the program which you did not get directly from me for your personal use, is considered software-piracy.

The personalized version may not be transferred, sold or exchanged to another person or organization. It is solely for the use of the registered person.

You may not use any "patches" for Future Drive Accelerator or publish them (regardless whether they are in text, binary or any other form), except with explicit permission by me for the purpose of updating. Using patched or modified versions of this program is considered software-piracy.

NO WARRANTY

There is absolutely no warranty for this software. Although the author has paid attention on security of data, compatibility and speed while developing this software, he can give no warranty that this program is 100% bug-free. You are using this software solely on your own risk. The author cannot be held responsible for any damages or loss of data that may be caused by this program.

DISTRIBUTION

The demo-version package is "freely distributable". It may be copied on any media that is used to distribute free software, for example: FD-disks, CD-ROMs, FTP-server and BBS systems.

The full version is not to be distributed.

No programm, document or file of this software package, partly or completely, may be distributed with another software package without the written permission of the author.

The demo-version may only be distributed complete and unchanged.

To make sure that the archive is its original state, distributors should only use the original archives:

Aminet: fda.lha (<http://de.aminet.net/pub/aminet/disk/cache/fda.lha>)

World Wide Web: fdaupdate.lha (<http://home.pages.de/~MartinTauchmann/> ↔ fdaupdate.lha)

---



Programs and documentation may not be modified. The only exception is the use of archiving software like LHA, LZX, ZIP or TAR-GZIP/BZIP2, as long as the files can be restored unaltered.

There is no upper limit for distribution costs (cost for disks, tapes or CD-ROMs, or for duplicating them). Such limits have proven harmful for the idea of free software. In some cases, software has been removed instead of lowering the price of a disk below the limit.

Although the author has not set such a limit, he wants to make clear his opinion on the topic:

- \* This demo software should be available free to everyone, wherever this is possible.
- \* If you bought this demo software under normal conditions from a PD dealer on a disk and paid more than 5DM/5\$, you have certainly paid too much. Please don't support such practices and try to find a better and cheaper source for your software.

#### RESTRICTIONS OF USE

Future Drive Accelerator may only be used in the way intended by the author, this means it may only be executed on Amiga-computers running AmigaOS. Reassembling, reverse engineering or translation of the source code is forbidden.

The documentation and the program texts of Future Drive Accelerator are protected by the same copyright as the program itself. This means the documentation or program texts may not be altered or translated.

To avoid any misunderstandings: You MAY NOT translate the texts or documentation for Future Drive Accelerator and distribute them. You must be authorized by me as an official translator. Unauthorized translations of texts and documentation are illegal, harm the copyright and will be removed from public software archives.

No program, document or file from this software package may, partly or completely, be used on a machine which is

- \* used for the research, development, construction, test or production of weaponry or any other military equipment. This includes machines which are used for training purposes.
- \* used by persons, who accept, support or use violence against other persons (e.g. foreigners).

## 1.16 FDA/Author

Where to send bug reports, comments and orders?

\*\*\*\*\*

The author can be reached through the following addresses:

---

Postal adresse:

Martin Tauchmann  
Scheffelstr. 49  
79102 Freiburg im Breisgau  
GERMANY

E-Mail:

<MartinTauchmann@bigfoot.com>

Sometime you can find me in IRC at "irc.uni-stuttgart.de" in the "#amiga"-channel as NickName "Gaddis".

There is also a Future Drive Accelerator homepage in the World Wide Web, with cyberlinks to "Super Find Engines" and many other usefull cyberlinks:

Germany (<http://MartinTauchmann.home.pages.de>)  
U.S.A. (<http://bigfoot.com/~martintauchmann/>)

The Pretty Good Privacy (PGP) "PublicKey" is available with Finger, or via WWW (<http://horowitz.surfnet.nl:11371/pks/lookup?op=index&search=0xF74B8D1D>).

ICQ, aka UIN is on my HomePage.

## 1.17 FDA/Features

Compatibility, Features of Future Drive Accelerator

\*\*\*\*\*

- \* Accelerates all kind of media e.g.\*: Harddisk-, Floppy-, Compact-, ZIP, MagnetOptical- or SyQuest-drives, almost like a RamDrive.
  - \* Uses the free memory as cache , the program reacts automatically on changes in memory resources, so that you will always get the maximum speed for your drives. Even "resources-hungry" programs will get enough memory.
  - \* Minimizes the overall seek time required to read or write data from or to disk. Outstanding I/O requests are ordered such that they can all be performed "with one sweep" of the disk head assembly, from the highest to the lowest disk address (Elevator seeking).
  - \* Gentle, parallel reading and writing in Multitasking.
  - \* Smart-Power-Technologie: Minimizes the number of disk-accesses.
  - \* SmartCache: Read-ahead of blocks.
  - \* When disks are removed, the cache is only removed if necessary. When disks are re-inserted, the cache will be used again.
  - \* No fragmentation of memory. (Opposite to DynamiCache.)
  - \* Can possibly save memory, because dos-buffers are not required anymore.
  - \* Power-LED flashes when accessing cache.
-

- \* Verify is as fast as in a copy-program, because data is verified in the background while writing. (the processor isn't used much while writing anyway).
- \* If DiskSafe is installed, the cache will be written before a reset or system-crash restarts the computer. See  
Requirements  
.
- \* Supports DiskExpander  
(<http://de.aminet.net/pub/aminet/util/pack/epul4.lha>),  
Virtual-Memory-Manger (VMM),  
XFH (<http://de.aminet.net/pub/aminet/util/pack/XFH.lha>) temporal files and  
World-Wide-Web browsers.
- \* Supported devices: (probably all
  - scsi (<http://www.amiga.de/files/index.html>), 2nd.scsi, NewStyleDevice,  
atapi (<http://de.aminet.net/pub/aminet/disk/misc/IDEfix97.lha>),  
cybscsi,
  - trackdisk,  
floppy (<http://de.aminet.net/pub/aminet/disk/misc/floppy43.lha>),  
diskspare (<http://de.aminet.net/pub/aminet/disk/misc/Diskspr3.lha>),  
hackdisk (<http://de.aminet.net/pub/aminet/disk/misc/NewHackdisk.lha>),  
mfm.device ((C)CrossDOS),  
messydisk (<http://de.aminet.net/pub/aminet/misc/emu/msh-156.lha>),
  - fmsdisk (<http://de.aminet.net/pub/aminet/disk/misc/fmsdisk.lha>),
  - xpkdisk ([http://de.aminet.net/pub/aminet/util/pack/xpkDisk37\\_8c.lha](http://de.aminet.net/pub/aminet/util/pack/xpkDisk37_8c.lha)),
  - cd.
- \* Supported FileSystems: (All knownn)
  - FastFileSystem (FFS),  
V44.5 (<http://de.aminet.net/pub/aminet/disk/misc/ffstd64.lha>)  
V43.20 (<ftp://ftp.amiga.com/pub/>)
  - ProfiFileSystem1+2 (PFS)  
(<http://de.aminet.net/pub/aminet/disk/misc/pfs95.lha>),  
HomePage (<http://www.greed.nl>)
  - AmiFileSafe (AFS)  
(<http://de.aminet.net/pub/aminet/biz/demo/afsdemo159.lha>),
  - SmartFileSystem (SFS) (<http://www.xs4all.nl/~hjohn/SFS/>),
  - MessyFileSystem (MSD)  
(<http://de.aminet.net/pub/aminet/misc/emu/msh-156.lha>),
  - CrossDOSFileSystem (MSD) ((C)CrossDOS),
  - Berkeley (NetBSD LinUX) Fast FileSystem (BFFS UNI\02)  
(<http://de.aminet.net/pub/aminet/misc/emu/bffs1.3.lha>).

and compatible, furthermore all MultiUser-"clones".

---

- \* Supports FileSystems with a variable block-size.
- \* Supports harddisks with a capacity of 4 GigaByte or more.
- \* Protects partitions beyond the 4 GigaByte "barrier" from faulty accesses.
- \* Is the fastest cache program. Accelerates harddisks by the factor 2-20, floppy disks by the factor 2-997.

FileSystem installation  
How to use harddisks bigger than 4 GigaBytes

DataSafety  
What you should know when using ProfiFileSystem-2 and ↔  
SmartFileSystem

SCSIdevice installation  
Better use for ATA[PI] drives

## 1.18 FDA/FileSystem installation

How to use harddisks bigger than 4 GigaBytes.

=====

Type VERSION HD0: into a shell, to find out if version 44.5 (<http://de.aminet.net/pub/aminet/disk/misc/ffstd64.lha>) or 43.X (<ftp://ftp.amiga.com/pub/>) of the FastFileSystems is installed.

The new FastFileSystem version (1) must be installed into the RigidDiskBlock (RDB) using HDToolBox. Copying to the L: directoy is not enough. (2)

If you have more than one harddisk on your Amiga, the FastFileSystem is loaded only from the Boot-Unit-HardDisk-RDB. So you have to install the new FastFileSystem into the Boot-Unit; but of course doesn't it do any harm if all Unit-HardDisk-RDB's are updated.

Reformatting of the partitionen is not required, this means the files remain accessible with the new FastFileSystem (<http://de.aminet.net/pub/aminet/disk/misc/ffstd64.lha>). The new FastFileSystem works of course with IDE-drives, too.

How do you update the FastFileSystem?

Start the program SYS:Utilities/HDTools/HDToolsBox:

Select your Boot-HardDisk, 'Partition Drive', 'Advanced Options', 'Add/Update...', now you can see which version is running in your Amiga, 'Update File System...', enter l:FastFileSystem, 'OK', now it should read Version: 44 and Revision: 5, 'OK', 'OK', 'OK', 'Save Changes to Drive', 'Exit'.

DataSafety

What you should know when using ProfiFileSystem-2 and ↔  
SmartFileSystem

SCSIdevice installation

Better use for ATA[PI] drives

----- Footnotes -----

(1) or SmartFileSystem\_SCSIdirect, ProfiFileSystem-2\_SCSIdirect.

(2) FastFileSystem V44.5 is not compatibele with vdisk.device,  
statram.device, diskspare.device and fms.device

## 1.19 FDA/DataSafety

DataSafety

=====

The datasafety of the FastFileSystem is extended with Write Async in the case of a power cut.

The ProfiFileSystem-2 and the SmartFileSystem provide datasafety even in the case of a power cut, the medium is always "validated".

The medium is kept "validated" by saving the structure-organizing data to the disk immediatly.

=> You could image this as a tree, whose branches have always to be present, the leaves (files) may grow or fall off without harming the tree itself. New leaves are written to the "list of existing leaves" when the completely grown up. => Of course, files which were saved during the power cut are lost.

To maintain a valid structure on the medium, the FileSystem must not loose control about the moment of writing, this means the structure must be written "synchron".

=> Write Async may not be activated, to ensure datasafety during a power cut.

Write Async can be activated, if there is enough free memory available to cache the WHOLE write-process.

=> The medium is always "validated".

In future versions, using a new FileSystem, datasafety will be maintained during a power cut, even with low memory, using Write Async. The important structure data (tree) is written "Synchron" and the files (leaves) "Asyncron".

FileSystem installation

How to use harddisks bigger than 4 GigaBytes

SCSIdevice installation

Better use for ATA[PI] drives

## 1.20 FDA/Future

What will happen to Future Drive Accelerator?

\*\*\*\*\*

The oracle foretells:

- \* Porting to the new AmigaOS QNX.
- \* New memory-routines. See  
Known bugs  
.
- \* Better cooperation with PFS-2 to ensure datasafety during a power-cut. See  
DataSafety  
. Furthermore a speedup, because PFS-2 reads and writes  
directly in the cache.
- \* Translating the documentation in several languages.
- \* Porting of oo2c (<http://www.uni-kl.de/OOC/>) to the Amiga, which makes it  
possible, thanks to GNU-C (GCC), to develop Oberon-2 programs for any  
platform. Oberon-2 is almost identical to Amiga E, ADE 95 (gnat),  
Modula/Pascal and Cluster.
- \* Porting of Garbage Collector ([http://reality.sgi.com/boehm\\_mti/](http://reality.sgi.com/boehm_mti/)) to the  
Amiga. Replaces C malloc, C++ new as well as C string (cord) which is used  
for fast string operations.
- \* New ixemul.library version.

## 1.21 FDA/History

Development history of Future Drive Accelerator

\*\*\*\*\*

1.4, Release date 7-Mai-99

- \* Brandnew documentation. (Guide, HTML, PS, DVI)
- \* Size of Track is now variable.  
=> Possible to read more data, before they are needed (read-ahead).  
=> No fragmentation of memory, if all Units set to the same Size of  
Track.
- \* Support Virtual-Memory-Manger (VMM). Make in VMM-Prefs Code=No  
Data=No Program=FDA.

- \* Fixed, could hang sometimes 1/1.000.000, while writing back Cache. Because, AbortIO of the Timer Device of OS3.0 has a bug. The Vertical-Blank-Interrupt can jump between the CheckIO and AbortIO of the time-request.  
=> Now doesn't use AbortIO. Restart the Timer if it came back to early.
- \* Fixed, Checksum-Error, if HD has a capacity more than 2GB (2^31 "SignedLongWord border").  
Because, Oberon has no support for ULongWord (Unsigned).  
Replaced all DIV in uDIV, and MUL in uMUL.  
IF (highCyl+1) \* surfaces > MAX(LONGINT) DIV ASH(SizeOfTrack,-1) THEN  
/\* HD > 4 GB \*/  
Thanks to Timo Murzo (Master.T.M)            Sysop of Unity Mailbox Hamm  
Thanks to Michael Kilimann  
Thanks to Denis Zwornarz  
=> Current limit is 1126 GB.
- \* No further translation of SCSI-direct commands into TrackDisk commands.  
If FDA is called with a SCSI-direct command, it uses the same command.  
=> FFS V44.5 and the special SCSI-direct Versions of PFS-2 and SFS, have no limits (1126 GB) about the HardDisk size. See

#### FileSystem installation

.

- \* If the cache (whole memory) is full of data and any other program needs memory, the cache will be written back (flush) and than is memory free again.
- \* Update-Task (writing back) priority is now one higher than Unit-Task (read/write).
- \* Fixed, Enforcer hits.  
Thanks to Michael Kilimann
- \* Added ChangeInterrupt. CD-Drives need this, to detect a DiskChanges. Excluded 'mf.device' V40.9 (21.05.93), 'multidisk.device' and 'xpkdisk.device' V37.8, because they had a BUG while removeChangeInt. Device developer: Please, take a look at HackDisk.device Assembler-SourceCode.  
Thanks to Marc Michael (yogi)
- \* Dos-Buffers set to 7.
- \* Fixed, Dos-Buffers not freed if "QUIET" was used.
- \* Supported Berkeley (NetBSD LinUX) Fast FileSystem.  
=>protStatus Command detect "Disk Inserted" and Motor off interpreted as "update" Command.  
Set the Dos-Buffers of Berkeley (NetBSD LinUX) Fast FileSystem to 456, because lower values made read errors (found with DiskSpeed V4.2).
- \* One timer for one Partition, not only one for the whole Unit.
- \* Fixed, don't turn off the DiskFloppy motor at some systems.

- Motor command is again back in the waiting queue.  
Developer: Imagine, if you're using SendIO instead of DoIO, the execution is async not only by reading and writing also with the changeState, motor, protStatus, remove, changeNum ... commands.  
Thanks to Herbert Pittermann  
Thanks to Jörg Liebelt
- \* Spared one uDIV Processor instruction. (A modulation and a division in an single uDIV instruction.)  
=> Little bit faster.
  - \* Little speed up, if an SCSI-direct FileSystem is used.
  - \* Uses exec.GetMsg only if an Message is available (Port.msgList.head^.succ<>NIL).  
=> Little bit faster (0.44%-0.51%).
  - \* Fixed, printed -1, at verify requester as Track number.
  - \* Fixed, verify retry.
  - \* Fixed, no error number result if an update error exists in Sync-writing-mode.
  - \* Fixed, can't find the icon. <QUIET> Tooltype now working.  
=> No window opening, if it's started from WBStartup-Drawer.  
# Thanks to Harald Wünsche
  - \* Windows are now simple-refresh.  
=> spares ChipMemory.
  - \* Reduced Stack allocation.
  - \* DSG (Benchmark-Statistics) is now able to read DiskSpeed V4.2 results, but it can't display values greater than 9.9MB.
  - \* Added Blizzard-IV (030 50Mhz) Accelerate-Card benchmarks in the guide.
  - \* Added PPC604 233MHz 060 50MHZ Accelerate-Card benchmarks in the guide.
  - \* Preferences:
    - Renamed the Options.
    - Removed "Write-Retention off".
    - Replaced "ASync-update-writing" with "Write async = 0 sec".
    - Added "Write as late as possible", for Cache-directories of WWW-Browsers.
    - Added "Write for temporary", for t: env: directories.
    - Now, quick toggle device with Shift+LeftMouse.
    - Converted "low Track" to "low Cylinder".
    - Device-List gadget uses the default font, fall back to the
-



topaz.font, if the other text font is proportional or the default font is also proportional.  
Thanks to Andrew Mowatt  
Thanks to Frédéric Laboureur (Fred) AlphaSOUND - FANTAISIE Software (1998)

- Added "Size of Block" of FileSystem in Info.
- Used really New-Look-Menus.
- Fixed, menu "LastSaved" and "Restore".
- Fixed, Argumente "USE" and "SAVE".
- Reinserted "USE".
- Fixed, division by zero trap, if no FastMem available.  
Thanks to Flemming Steffensen
- Fixed, division by zero trap, if "blocks per track" or "surfaces" are zero. (NewPortHandler)  
Thanks to Flemming Steffensen
- Fixed, trap if BlockSize<>0.  
Thanks to Carsten
- Fixed, no NewStyleDevice detection if another unit as zero are used.

\* View:

- View uses the default font; if it's proportional and the size isn't 8x8, it falls back to the topaz.font.  
Thanks to Herbert Pittermann  
Thanks to Helge Böhme
- Use New-Look-Menus.  
Thanks to Frédéric Laboureur (Fred) AlphaSOUND - FANTAISIE Software (1998)
- Fixed, bad DiskName if another "Size Of Block" as 512 is used.

\* In the Demo Version is writing now possible, but only the half free memory can be used by two drives as cache.

\* Price increased by 4.99DM to 19.99DM.

1.2, Release date 20-Aug-98

- \* Speed up Read/Write little bit.
  - \* Preferences: 'Not used Memory' Proportional-Gadgets are now in Percentage and KiloByte.  
Special thanks to Andrew Mowatt
  - \* Better communication between the filesystem and FDA.  
Should fix occasional hangings in the previous release.
  - \* Fixed, detect Partitions after 2-GB as 4-GB Partitions. Support 4-GB
-

HDs is more possible.

Thanks to Timo Murzo (Master.T.M)            Sysop of Unity Mailbox Hamm

\* Preferences

- Used New-Look-Menus and scale checkboxes.

Thanks to Frédéric Laboureur (Fred)    AlphaSOUND - FANTAISIE  
Software (1998)

- Unnecessary 'Can't open x.device' removed, if it is not a New  
Style Device.

Thanks to Marc Michael (yogi)

\* Nicer looking MWB icons.

Thanks to Frédéric Laboureur (Fred)    AlphaSOUND - FANTAISIE Software  
(1998)

1.0, Release date 20-Jul-98

- \* Added SmartFileSystem benchmarks in the guide.

- \* Write operation a little bit faster.

- \* Fixed, StartUp RangeCheck trap, if Size of Track > 131072.

- \* Dos-Buffers set to 20.

- \* Supports NewStyleDevice: (NSD) 64-Bit Commands (4GB border).

- \* Supports scsiCmd (4GB border).

\* Preferences

- Include more "big" HDs.

Thanks to Timo Murzo (Master.T.M)            Sysop of Unity Mailbox Hamm

- DeviceCompatible removed.

0.98, Release date 04-Jul-98

- \* Supports Partitions after the 4GB border (not tested).

- \* Speedup Read & Write operations.

\* Preferences

- Includes LateBinding-Devices.

- Preferences: Removed buggy "USE".

0.96, Release date 25-Mar-98

- \* First public release @ the AmiNet.

## 1.22 FDA/Other Products

Other products

\*\*\*\*\*

---

From the same author:

- \* Future Copper Producer (<http://de.aminet.net/pub/aminet/gfx/edit/FCP.lha>)
  - Convert Pic -> CopperList (6BitPlane -> 0 BitPlane CopperList)
  - CopperListEditor
  - CopperListSearcher
  - Full Modula-2 SourceCode
- \* Telekom Bill (<http://de.aminet.net/pub/aminet/comm/misc/TelekomBill.lha>)  
German Phone-Bill calculater for WG's
- \* Active Window Picture (<http://de.aminet.net/pub/aminet/gfx/show/ActiveWinPic.lha>)  
displays pictures in any window, especial SHELL.
- \* File 2 Partition (<http://de.aminet.net/pub/aminet/misc/unix/File2Partition.lha>)  
Spares memory if LinUX is installed, stores files direct to HD, Disks or any LogicalDevice
- \* Is Inserted? (<http://de.aminet.net/pub/aminet/util/boot/IsInserted.lha>)  
StartUp-Check if a Disk inserted then start BootUte, or any ...
- \* BrainBird (<http://de.aminet.net/pub/aminet/mods/slow/BrainBird.lha>)  
Shaman drums to meditate and 14 Ambient/NewAge/Music concrete Songs.
- \* Exec.library disassembly (<http://de.aminet.net/pub/aminet/dev/asm/ExecDis.lha>)  
A commented disassembly of the exec library 1.2.
- \* PasTeX ShowDVI-SuperHighRes EpsonMedium/Low (<http://computer.freepage.de/tauchmann/PasTeX-SuperHighRes.lha>) (5.1 MB)  
SuperHighRes & Epson medium pk-fonts, other resolutions possible.  
=> Display 9PinPrinter "Quality" on Screen.

From other authors (in Aminet):

- \* Better Amiga feeling
  - Copper-rainbows on ALL pubscreens (<http://de.aminet.net/pub/aminet/util/wb/Copper-Demon.lha>).  
Needs ScreenNotify.library  
(<http://de.aminet.net/pub/aminet/util/libs/ScreenNotify10.lha>),
  - PersonalPaint (<http://de.aminet.net/pub/aminet/biz/cloan/PPaint64.lha>)  
AnimBrush (16 colors) as Mouse-Pointer  
(<http://de.aminet.net/pub/aminet/gfx/aga/AnimPoint10.lha>),  
needs AGA/3.0 needs QMouse  
(<http://de.aminet.net/pub/aminet/util/cdity/qmouse290.lha>)  
to blank pointer, because MultiCX can't do it.
  - Animated Busy Pointer Hack (<http://de.aminet.net/pub/aminet/util/boot/pointerx.lha>).

- Time and Mem (<ftp://ftp.uni-stuttgart.de/pub/systems/amiga/amok/amok080/> ↔  
TimeAndMem.lha)  
in the Shell-Prompt.
  - AntiTopaz (<http://de.aminet.net/pub/aminet/util/misc/AntiTopaz.lha>)  
Substitutes topaz with system default font.
- \* Relax Music
- DI-\* "MagneticNorth" ([http://de.aminet.net/pub/aminet/mods/slow/DI-\\*.lha](http://de.aminet.net/pub/aminet/mods/slow/DI-*.lha) ↔  
)

## 1.23 FDA/Credits

The author wants to thank...

\*\*\*\*\*

The development would have been impossible without the feedback of some Future Drive Accelerator users. Many ideas and features came from these sources...

So I'd like to thank the following persons:

For Alpha-/Beta-Tests, ideas & bug-reports:

Frédéric Laboureur, Michael Kilimann, Denis Zwornarz, Andrew Mowatt, Marc Michael, Herbert Pittermann Kisses for you sweet Kids, Harald Wünsche, Timo Murzo, Jörg Liebelt, Flemming Steffensen, Helge Böhme, Andreas, Carsten.

For the translations:

The Amiga Translators Organization (ATO) (<http://ato.vapor.com>)  
Jens Neubauer <jens.neubauer@gmx.de>

For proofreading:

Gregor Knechtges  
Heiko Hayn <Smeagel@gmx.net>

Malcolm Harnden

For supporting the PPC Amiga.

Fred Fish

Without your excessive commitment for the Amiga, I hardly would have gotten those bits and bytes to feed my curiosity. Your new GeekGadget (<ftp://ftp.unina.it/pub/amiga/geekgadgets/amiga/m68k/snapshots/current/>) Project with the GNU ports is very praiseworthy. The text you read at the moment has to be partly credited to Fred Fish because it is written in Texinfo.

Reinhard Spisser and Sebastiano Vigna

for the Amiga-port of "makeinfo".

Michael Marte, Hamish Macdonald, Geert Uytterhoeven, Chris Lawrence,

Joerg Mayer, Martin Apel, Richard Hirst, Roman Hodek, Thomas Kruse, Benjamin (Benni) Lorenz, Odd-Jarle Kristoffersen, Jes Sorensen, Ron Flory  
... (MC 680xx LinUX)

I can't find words.

Kamil Iskra, Philippe Brand, Fred Fish, Leonard Norrgard, Hans Verkuil, Gunther ←  
Nikl, Anders Wegge Jakobsen (GNU C Compiler)  
You made it possible to program for every platform.

Dirk Busse (CopyMemQuicker)  
Thanks to your optimising, the cache has become even more faster. See

Speed up

.

Matthew Dillon  
Without your DME (programable text-editor) maybe I had never started  
typing.

Friedjof Siebert  
Without your damn-fast Oberon-compiler, it would have been only half as  
much fun.

Amiga Modula Oberon Klub Stuttgart AMOK  
Your enthusiasm dragged me on. Where do you get all these good ideas from?

Niclaus Wirth  
Brought light into the darkness, finally one can read the programs.

Jonathan Potter  
Please stay with us. From ScreenX to DOpus, you evolved very much.

Ralph Babel  
Very dry, interesting book, in which sect are you now?

Commodore, AmigaInc. ...  
Don't dare to drop the Amiga like the Hippis the '68er. The Amiga is the  
Harley among the platforms.

Telekom  
He, I still don't have a modem.

Quasar (White Box), CodX (Dialer/UnlimitedAcces)  
Really clever how you fooled the Telekom back then.

William Gibson  
Great books, I still don't understand one word.

William Gaddis  
Master of the dialogue, pity that your time is over.

Nico François  
PowerSnap is just great! RequesterTools anyway. PowerPacker was a must  
in times when buying a harddisk costed a fortune.

Georg Hörmann XFD  
Fixed the old bugs in the decrunchers.

ASDG FACC  
Your FloppyAccelerator inspired me.

---

TURBOBRAIN (D-Copy)

Your D-Copy (<http://de.aminet.net/pub/aminet/disk/misc/DCopy31.lha>) finally brought X-Copy to an end.

Georg Heßmann

Your PasTeX made the Amiga able to print.

? SoundTracker+

The author is unknown, so I just thank Tracer and DOCTOR MABUSE and UNKNOWN of D.O.C and MnemoTrON / Silicon League, TIP of THE NEW MASTERS.

BAMIGA SECTOR ONE, RED SECTOR ...

Great intros, just very old.

Kai Nickel (MathX)

Another remnant of AMOK. Abitur (school leaving examination) is impossible without your program.

TRIAD (TitanicsCruncher)

Without your cruncher, one would have to buy RAM all the time.

Bert Jahn WHDLoad (<http://www.fh-zwickau.de/~jah/whdload/>), Jean-François Fabre ←  
JST (<http://perso.club-internet.fr/jfffabre/amiga/patches.html>)

Good work, finally the classic games work with AGA, too, and can be loaded quickly from the harddisk.

BullFrog (Populous, Powermonger...)

It is real fun to play god.

John Matthews (MultiPrint)

What did I have to suffer from print-programs until I found yours! Well, the handling could be easier.

BootX VirusX VirusZ ...

I believe it was you who killed these poor viruses; and if not you, then it was OS2.0.

Zeitschrift Computing C-16

I find it impossible to print programs on dozens of pages, which you had to type into your computer to play something.

Commodore C-16 PLUS 4

Was fun, especially because you could press some keys and break and disassemble and debug any given program.

Forum InformatikerInnen fuer Frieden und gesellschaftliche Verantwortung FIFF e.V.  
Pretty Good Privacy PGP

Thanks for telling the people about the governmental fooling.

Michael Sinz (MKSoft Development), Bryce Nesbitt

Without DiskSpeed, no one had told me it was getting better.  
The Enforcer is absolutly necessary for debugging.

Martin Mares (MJSoft System Software)

---

Your Resident Module Launcher, and SKick are really good, now you don't have to buy several ROMs each time.

Valenta Ferenc (Copper-Demon)  
Great feeling.

Sylvain Rougier (ParM)  
Your ParM is my ToolManager.

Stefan Becker (ToolManger)  
I used the structure of your documentation.

Richard Körber (PatchWork)  
See  
Known Bugs  
.

Thomas Richter (SaferPatches)  
DiskSafe (<http://de.aminet.net/pub/aminet/disk/salv/DiskSafe.lha>) is a nice little tool.  
Your  
SaferPatches (<http://de.aminet.net/pub/aminet/util/misc/SaferPatches.lha>) solved the problem!

Harry Sintonen (HackDisk)  
Your HackDisk assembler-sourcecode answered my questions.

Urban Dominik Müller, Dirk Stöcker, Bryan Ford and Christian von Roques  
Your XPK-system is without competition.

all users who decided to register Future Drive Accelerator.

## 1.24 FDA/Speed up

How to speed up Future Drive Accelerator even more

\*\*\*\*\*

So you can make Amiga faster.

Install a CopyMem(Quick) (1) Replacement for your processor type:  
68000 (<http://de.aminet.net/pub/aminet/util/boot/COPMQR28.lha>)  
68020 (<http://de.aminet.net/pub/aminet/util/boot/CMQ030.lha>)  
68040+ (<http://de.aminet.net/pub/aminet/util/boot/CMQ060.lha>) The MCP replacement shouldn't be used, because it is slower than these versions.

Set the SCSIsynchron-Flag in the RigidDiskBlock of your boot-harddisk with RDBFlags (<http://de.aminet.net/pub/aminet/disk/misc/RDBFlags-1.3.lha>).

Don't use ChipMemory as cache, and set not used ChipMem in the preferences, to 100%. See

Das Hauptfenster  
.

If you use the program PoolMem, start it with the argument NoRamReverse.

SCSIdevice installation  
Better use of ATA[PI] drives

TurboBoards  
General speedup for turboboards

----- Footnotes -----

(1) CopyMem(Quick) is used to copy data between cache and system memory.

## 1.25 FDA/SCSIdevice installation

Better use of ATA[PI] drives  
=====

You don't have AmigaOS 3.1 and want to install the newest update of the (1) scsi.device (<ftp://ftp.amiga.com/pub/>) to get a better performance? (especially together with ATA[PI] drives)

Attention! There is no guarantee for this hack. (2) The modified file may not be distributed.

The hack works on an 1200 with OS 3.0.

1. Rename the file a300.ls.strip, if you use an Amiga 1200 (3) , to scsi.device, and copy it into the Devs: directory.
2. Load scsi.device V43.xx into a file-monitor:  
Search for \$0C6C0027. The next value is \$0014 6516. Replace \$6516 by \$6026.
3. Get  
AddModule (<http://de.aminet.net/pub/aminet/util/boot/NewAlertH.lha>).  
In the first line of your s:Startup-Sequence write:  
RUN <>NIL: c:AddModule <>NIL: DEVS:scsi.device CLASS 1 PRI 10 INIT ;V43  
CLASS xoper e flags

After the second reboot, the new scsi.device is loaded.

----- Footnotes -----

(1) The hack als works with  
FastFilesystem V43.20 (<ftp://ftp.amiga.com/pub/>)

(2) The hack removes an alert which informs the user that no OS3.1 is installed.

(3) If you have another Amiga, please read the readme text in the update-archive, to find out which file is the best for you.

---



## 1.26 FDA/TurboBoards

General speedup for turbo boards  
=====

You have a turbo board, e.g. a Blizzard-IV with Extra Fast Memory?

Is the `exec.library "function-jump-table"` (AVL) in the Chip Memory? (Can be found out using XOper or FastExec.)

Get FastExec (<http://de.aminet.net/pub/aminet/util/boot/FastExec29.lha>). Start it with:  
FastExec SysInfo

Is the output for `SysStkUpper $XXXXXXXX` a value greater than \$00200000 if you have 2MB ChipMemory, or \$00100000 if you have 1MB ChipMemory?

If not, then the ```supervisor stack``` is in Chip Memory. This slows down the "task-switching".

Insert this line in your `s:Startup-Sequence`, after `AddModule` (if present):  
FastExec REBOOT FASTSSP FASTMEM

## 1.27 FDA/Mark Bad Memory

How to use bad memory  
\*\*\*\*\*

Do your programs crash randomly?

Then your RAM-modules may be faulty. Especially PS-2 (SIMM) modules are very vulnerable to "static electricity".  
Or you have some unused RAM-modules laying around?

No need to worry, like on a harddisk, you can mark bad memory and exclude it from usage.

But first we have to know where exactly the memory is faulty. For this purpose there is an excellent program called MemTest (<http://de.aminet.net/pub/aminet/util/misc/MemoryTest.lha>), which should be started without booting (as much free memory as possible).  
Beforehand, the "DataCache" of the CPU should be disabled with

```
CPU NODATACACHE NODATABURST NOEXTERNALCACHE
```

. Now start the "Rotate 32" test and save the result.

Now get Allocate (<http://de.aminet.net/pub/aminet/dev/misc/allocate.lha>).

Insert at the beginning of your `S:Startup-Sequence`:

```
resident c:Allocate pure
Allocate <>NIL: 68900000 100000
Allocate <>NIL: 68B00000 100000
resident Allocate remove
```

The hexadecimal addresses should, of course, contain the bad memory areas. (Be generous, don't be stingy with a few 100KB or MB (depending on the chip).)

This works with Linux, too:

Create a file, where you insert all areas which work 100% okay. For example

```
2097152
0x68000000 9437184
0x68A00000 1048576
0x68C00000 3670016
```

and start AmiBoot with -m FileName.

## 1.28 FDA/OS more reliable

How to make the Amiga more stable

\*\*\*\*\*

Do your programs crash with a Guru 4 (Instruction error) or \$1000005 (Memory corrupt) ab?

The reason could be a too small stack. Every System has a different stack usage, because different programs run in the background, and change system-routines.

If several programs change the same system-routines, this may result in an stack overflow

- which can destroy the free-memory-list,

- or the return address of a subroutine is gone after a task-switch,

- or even other programs are changed accidentally (Enforcer/CyberGuard-Hit).

Even if only one program changes a system-routine and doesn't use stack itself, there are at least 4 Bytes used.

Luckily there is

StackAttack (<http://de.aminet.net/pub/aminet/util/boot/StackAttack.lha>), Which gives almost every program a little more stack.

example installation in the s:Startup-Sequence:

```
StackAttack ADDSTACK=512
```

## 1.29 FDA/Known Bugs

Known bugs

\*\*\*\*\*

---

If you think you found a bug in Future Drive Accelerator, please send a description see

description  
to the author see  
Autor  
.

Here is a list of known bugs and problems:

Bugs:

- \* ABackUp has a problem with the RAM-Disk patch of Future Drive Accelerator V1.4.  
=> If a file is packed with XPK and there is no space in the RamDisk, ABackup thinks the file is 2GigaByte large.  
Will be fixed in the near future, when the author has completely rewritten the memory-routines.
- \* AvailMemory(largest) gives a value that is too small.  
=> There is a larger continuous block; so "not used FastMemory" can be set to 1%.  
The real value can be determined if you start Avail from the shell, then quit FDA, and again start Avail.  
Will be fixed in the near future, when the author has completely rewritten the memory-routines.
- \* If the "Size of Track" is different from disk to disk, the memory will be fragmented.  
Will be fixed in the near future, when the author has completely rewritten the memory-routines.

Not real bugs:

- \* If Not used ChipMemory, see  
    MainWindow  
    is set to 100%, no track can be  
moved to make room.  
=> The track is removed from the cache.  
Will be improved soon, when the author has rewritten the memory-routines.
  - \* Doesn't support AbortIO, CloseDevice yet.
  - \* Supports, but not optimal, AllocMem(reverse).  
=> AllocMem reserves a memory area which is the last free. Normally this is in an early region, because the cache is behind. See  
    Installation  
    .  
Will be fixed in the near future, when the author has completely rewritten the memory-routines.
  - \* ViNCed V3.63 doesn't use AllocEntry or AllocPooled from exec library, to maintain an own poolmemory, to bundle small memory allocations. (It replaces AllocPooled with an own routine.)  
=> The cache is very often flushed unnecessary. That's a pity, because for instance the horizontal scrolling is a nice feature.  
KingCON V1.3 makes no problems.
-

Will be fixed in the near future, when the author has completely rewritten the memory-routines.

- \* vdisk.device 2.7 (C) 1994-1997 by Etienne Vogt (like ramdrive.device) Doesn't work together, because vdisk does not use OS-memory functions. Is not that tragic, because it doesn't support FastFileSystem V44.5, too.

Future Drive Accelerator has been tested intensively with Enforcer/MungWall and PatchWork.

Patchwork has helped to figure out two very resistant bugs.

- \* CopyMem(Quick)  
size must not only be LongWordAligned (size MOD 8=0), but also Destination & Source. The bug appeared only after several 1000 times and caused chaos in memory.
- \* CopyMem(Quick)  
"memory areas are overlapping (incremental)" seemed to work, but sooner or later, there will be chaos in memory, too, at least with CopyMemQuickerV2.8. This doesn't mean that CopyMemQuicker is not a good program. See  
Speed up  
.

Problems of other cache-programs

- \* PowerCache
  - \* Has caused checksum error while writing, because Read/Write request are not put in a queue. Especially because the settings are saved to late before a reboot.
  - \* Cache usage is not flexible.
  - \* Doesn't re-use the cache when reinserting a disk.
- \* DynamiCache
  - \* Does not support Write Async.
  - \* Does not support SCSI-direct-FileSystems.
  - \* Does not support harddisk with more than 4 GigaBytes.
  - \* Doesn't re-use the cache when re-inseritng a disk.
  - \* Fragments the memory extremely.
  - \* Does not support AllocAbs and Allocate to free the cache for other programs.
  - \* If flush is executed (memory full), the cache is deleted, although the memory is not too short anyway.
  - \* Does not cache accesses from ArtStudioPro 3 and Imagine.

New Bug

Have you found a new bug?

---

DebugFiles  
Programs to aid the debugging

### 1.30 FDA/New Bug

New bugr

=====

1. Which version do you use?
2. What was set in FDAPref, see  
FDAPref  
? (Removeable Disk?, ...)
3. What says FDAPref, see  
InfoWindow  
, about the non-functioning partition?
4. If other programs do not work as they should, do they without FDA?
5. If DOS-checksum (Read/Write) error occurred, please activate FDAPref  
<Protect tracks in memory with checksums>, see

Protect tracks in memory with checksums  
. If FDA reports checksum  
errors, it is not a FDA BUG. Or try to install another FileSystem, if the  
harddisk has more than 4 GigaByte capacity. See  
FileSystem installation  
. Or remove static dust from your RAM-modules. See  
Mark Bad Memory  
.

6. How did the bug appear? How can it be reproduced?
7. Which hardware/software (Mem, OS, FileSystem, Device-Software) was used?
8. Was there a Guru-alert (error messages)?  
In FDA are Guru-number (error messages) built-in. These start with  
\$OFDA00##.

If there was another number, please start SegTracker from the  
Enforcer-package. Start Tnt or if possible Enforcer or replacement  
programs like CyberGuard (MC68060). Wait for the bug to show up again.  
Write down the error message.  
SegTracker is important because the author would like to know when the BUG  
occurs. See  
DebugFiles  
.

9. If something like this appears, please start Segtracker before.  
Guru #0005: Division durch 0

```

Dx 00007FFF 00000000 08C6FFFF 00000000 7FFFFFFF 00000000 081AAE54 ←
    00000000
Ax 081AADEC 08C5F9D6 08C5F9DA 08C5F88A 081AAE54 08C5FC34 08000AB0 08 ←
    C5F820
segment FDAPref
hunk      0
offset 0000365E
sr 0000
pc 08C553E6
<RETURN>

```

DebugFiles  
 SegTracker, Enforcer und Co.

### 1.31 FDA/DebugFiles

SegTracker, Enforcer und Co.  
 -----

Please read on if you have a processor with MMU, or want to know whether you have.

Needed files

Enforcer supports MC68060 (<http://de.aminet.net/pub/aminet/dev/debug/enforcer.lha>) ←

,

CyberGuard supports MC68060 DisASM ([http://de.aminet.net/pub/aminet/biz/p5/68060-V44\\_3.lha](http://de.aminet.net/pub/aminet/biz/p5/68060-V44_3.lha)),

MungWall to detect Bad written Programs ([http://de.aminet.net/pub/aminet/dev/debug/Mungwall37\\_64.lzh](http://de.aminet.net/pub/aminet/dev/debug/Mungwall37_64.lzh)).

needed to display output (Virtua Terminal) (Work also if the MultTasking is switched off), a replacement for Sushi (<http://de.aminet.net/pub/aminet/dev/debug/MungFriend.lha>).

How to run Debugging-Tools?

SegTracker (Needed for locate (Hunk-offset) the bug)  
 RUN Devel:Debug/Enforcer/SegTracker

Enforcer

MultiCX/RebootOff (if MultiCX is running)

RUN Enforcer SHOWPC VERBOSE DEADLY STACKCHECK AREGCHECK DREGCHECK RAWIO  
 (need MungFriend)

RUN Enforcer SHOWPC VERBOSE DEADLY STACKCHECK AREGCHECK DREGCHECK

FILE=CON:0/0/640/100/Enforcer/Auto/Close

LawBreaker (Any Output? Yes the MMU is working.)

CyberGuard

RUN CyberGuard SHOWPC VERBOSE DEADLY STACKCHECK AREGCHECK DREGCHECK

FILE=CON:0/0/640/100/CyberGuard/Auto/Close PCLINES=4 SHOWDISS

LawBreaker (Any Output? Yes the MMU is working.)

MungWall (Detect bad written Programms (Checksumme-Error))  
 RUN MungWall INFO SHOWFAIL SHOWPC SHOWHUNK SHOWSTACK NAMETAG

Start Output Display Buffer (Virtual Terminal) (MungFriend ON RawSer->CON:)  
 RUN Devel:Debug/MungFriend INSTALL SIZE 40000 trace flash nobells noserial

Convert, only, GuruNumber in Hunk-offset, doesn't need an MMU.  
 Devel:Debug/Tnt FORCE

How to show the output?

MungFriend Type to Window  
 Devel:Debug/MungFriend  
 >CON:0/0/696/200/MungFriendSerOutput/Auto/Close/Wait/SHELL TYPE

MungFriend Write to File  
 Devel:Debug/MungFriend Write `RequestFile DRAWER=SYS:T/  
 FILE=SerialOutput.txt TITLE="OutputFile" `

MungFriend Clear  
 Devel:Debug/MungFriend CLEAR

MungFriend Info (Is any inside?)  
 Devel:Debug/MungFriend INFO

MungFriend ON RawSer->CON After Reset/Dead-GURU: (OutPut is still alive)  
 Devel:Debug/MungFriend update trace

MungFriend OFF  
 Devel:Debug/MungFriend REMOVE

## 1.32 FDA/Technical

Technical data

\*\*\*\*\*

For curious people, who want to know everything.

- \* In Exec-Library are patched AllocMem (AllocVec, AllocPooled, CreatePool), Allocate (AllocEntry), AvailMem, AllocAbs and in the Device BeginIO.
- \* Memory for the tracks is reserved decreasing (reverse).
- \* The program was written in Oberon-2 and Assembler.
- \* One track requires 16 Byte in the cache-structure.
- \* Using Verify, memory of the size of one track is required per device.
- \* The TrackDisk64 and SCSI-direct commands support "only" 40-Bit
 

$2^{40} =$	1,0995 TeraByte	1125,9	GigaByte
$2^{64} =$	18446744,074 TeraByte	1,8889465931776e10	GigaByte

 The calculation is carried out with a "fast" 32-Bit division.

1226 GByte Festplatten will not be available until the 3rd millenium (by todays standards).

- \* Only an offset which is divisibile by 512 can be used. It would be possible to implement something else, but SCSI-drives don't support it anyway and there is no known program that doesn't read/write whole blocks (512 Bytes), so we can save a few bus-cycles here.
- \* These device commands are understood:

```
include:exec/io.h
read, write, update,
```

```
include:devices/trackdisk.h
format, extFormat, extRead, extWrite, rawWrite, extRawWrite,
extUpdate, motor, extMotor, protStatus, getGeometry, getDriveType,
getNumTracks, eject
```

```
trackdisk64 (http://de.aminet.net/pub/aminet/dev/misc/trackdisk64.lha)
read64, write64, format64
```

```
NewStyleDevice (NSD)
read64, write64, format64
```

Is used by FastFileSystem V43.x (<ftp://ftp.amiga.com/pub/>). => No problems with harddisks bigger than 4 GigaBytes anymore. See

How to use 4 GigaByte harddisks

.

Informations about these commands can be found here:

NSDDocs (<http://www.amiga.de/files/index.html>)

NSDPatch ([http://de.aminet.net/pub/aminet/disk/misc/NSDPatch43\\_20.lha](http://de.aminet.net/pub/aminet/disk/misc/NSDPatch43_20.lha))

```
include:devices/scsidisk.h
scsiCmd
```

SmartFileSystem\_SCsIdirect, FastFileSystem V44.5 und ProfiFileSystem-2\_SCsIdirect use this command instead of the old trackdisk read/write commands.

=> No problems with harddisks bigger than 4 GigaBytes anymore. See

How to use 4 GigaByte harddisks

.

Not all scsiCMD are used, because I don' have a documentation.

```
( SCSIProgrammer (http://de.aminet.net/pub/aminet/dev/misc/ ←
  SCSIProgrammer.lha) )
```

```
( (include:scsi/commands.h SCSI-2 include files) )
```

```
( Direct Access devices      =da )
( Write Once devices         =wo )
( CD-ROM devices             =cd )
( Scanner devices            =sc )
( Optical memory devices     =om )
( Sequential access devices   =sa )
```



```

( Printer devices           =prt)
( Processor devices        =cpu)
scsiREAD6                   =$08 ( da wo cd om ) (not tested)
scsiREAD10                  =$28 ( da wo cd sc om )
scsiREAD12                  =$A8 (   wo cd om ) (not tested)

scsiWRITE6                  =$0A (   wo om ) (not tested)
scsiWRITE10                 =$2A (   wo om )
scsiWRITE12                 =$AA (   wo om ) (not tested)

```

Has anyone a documentation for these commands?:

```

scsiREAD_BUFFER            =$3C ( da wo cd sc om sa prt cpu )
scsiWRITE_BUFFER           =$3B (   wo cd sc om sa prt cpu )
scsiUPDATE_BLOCK           =$3D (           om )

```

Programmers

What programmers should observe...

Default

Which values are the defaults?

ReturnNumbers

What are the return values?

FileSystem installation

How to use 4 GigaByte harddisks

DataSafety

What you should know when using ProfiFileSystem-2 and ↔  
SmartFileSystem

SCSIdevice installation

Better use of ATA[PI] drives

### 1.33 FDA/Programmers

What programmers should observe...

=====

1. Data, which shall be written using the DOS functions Read/Write, should be LongWordAlligned (adr MOD 4=0), because the processor can access them faster then. This also applies to data which is sent directly to a device. AllocMem, Allocate... automatically return an address that is LongWordAlligned. So you only have to pay attention if you divide a memory block manually.
2. Remember: If you use SendIO instead of DoIO, the command is executed Async. Not only reading and writing, but also changeState, motor, protStatus, remove, changeNum ... commands.

### 1.34 FDA/Default

Which values are the defaults?

=====

At the first start and after choosing <Edit/reset to Defaults> from the menu, these values will be used:

```

Create Icons                               = FALSE (OFF)

Not used FastMemory                         = 60 KB
Not used ChipMemory                         = 50 KB
FastMemFirst                               = TRUE (ON)
View color flash if track moved or deleted = FALSE (OFF)
Protect tracks in memory with checksummes  = FALSE (OFF)

HD           Async delay                    = 4 seconds
Disk        Async delay                    = 7 seconds
    
```

Device	Pri	Settings
DF0	100	Removeable Disk, Write Async, Verify write
DF1	100	Removeable Disk, Write Async, Verify write
DF2	100	Removeable Disk, Write Async, Verify write
DF3	100	Removeable Disk, Write Async, Verify write
DS0	80	Removeable Disk, Write Async, Verify write
DS1	80	Removeable Disk, Write Async, Verify write
DS2	80	Removeable Disk, Write Async, Verify write
DS3	80	Removeable Disk, Write Async, Verify write
PC0	60	Removeable Disk, Write Async, Verify write
PC1	60	Removeable Disk, Write Async, Verify write
PC2	60	Removeable Disk, Write Async, Verify write
PC3	60	Removeable Disk, Write Async, Verify write
PS0	40	Removeable Disk, Write Async, Verify write
PS1	40	Removeable Disk, Write Async, Verify write
PS2	40	Removeable Disk, Write Async, Verify write
PS3	40	Removeable Disk, Write Async, Verify write
CD0	20	Removeable Disk, WriteRetention
HD0	0	Write Async
HD1	0	Write Async
HD2	0	Write Async
HD3	0	Write Async
DH0	0	Write Async
DH1	0	Write Async
DH2	0	Write Async
DH3	0	Write Async

### 1.35 FDA/ReturnNumbers

Return values

=====

The return values can be used within a shell-script.

```

Sys:Prefs/FDAPref ENVARC:FDA-AfterBoot.prefs USE
IF WARN ;FDA is not running
    RUN Sys:System/FDA ENVARC:FDA-AfterBoot.prefs QUIET
ENDIF

```

```

Sys:System/FDAView >NIL: Kill-FDA
IF NOT WARN ;FDA is running before
    RUN Sys:System/FDA ENVARC:FDA-AfterBoot.prefs QUIET
ENDIF

```

```

RUN Sys:System/FDA ENVARC:FDA-AfterBoot.prefs QUIET
IF $RC GE 5 ;FDA is running before
    Sys:Prefs/FDAPref ENVARC:FDA-AfterBoot.prefs USE
ENDIF

```

```

AlreadyRunning          = warn          (5)
PreferenceCancel        = error          (10)
PreferenceFDANotRunning = warn          (5)
NoDeviceCached          = fail+1        (20 +1)
CanNotCreatePort        = fail+2
ReadArgsError           = fail+3
CanNotReadPrefs         = fail+4
CanNotCreateTask        = fail+5
AllocSignalError        = fail+6
NoMem                   = fail+777-fail

```

## 1.36 FDA/Index

### Index

\*\*\*\*\*

```

4 GigaByte capacity <1>
  InfoWindow

4 GigaByte capacity <2>
  Features

4 GigaByte capacity
  FileSystem installation

ABackUp
  Known Bugs

AbortIO
  Known Bugs

accelerate
  Concepts

active
  DeviceWindow

```

---

AddModule <1>  
    SCSIdevice installation

AddModule  
    TurboBoards

Addresses  
    Author

AFS  
    Features

Alert  
    OS more reliable

Alloc Absolute, mark bad memory  
    Mark Bad Memory

AllocAbs (OS)  
    Technical

Allocate (OS)  
    Technical

AllocEntry (OS)  
    Known Bugs

AllocMem (OS)  
    Technical

AllocPooled (OS)  
    Known Bugs

Ami-FileSafe (AFS)  
    Features

Amiga 1200  
    Tested Systems

Amiga 3000  
    Tested Systems

Amiga 4000 (040)  
    Tested Systems

Amiga E (language)  
    Future

ArtStudioPro 3  
    Known Bugs

Assembler  
    Technical

Async  
    Programmers

---

---

Async delay  
  DeviceWindow

Async delay (button)  
  DeviceWindow

ATA(PI) <1>  
  Features

ATA(PI)  
  Tested Systems

Author  
  Author

AvailMem (OS)  
  Technical

AVL  
  TurboBoards

Bank transfer  
  Registration

Before Medium (button)  
  View

BeginIO (OS)  
  Technical

Benchmarks  
  Benchmarks

Berkeley (NetBSD-Linux) Fast FileSystem(BFFS UNI\\02)  
  Features

BFFS  
  Features

Blizzard-IV  
  TurboBoards

Block  
  InfoWindow

Buddha (IDE)  
  Tested Systems

Buffer memory type  
  InfoWindow

Bugs  
  Known Bugs

Cache <1>  
  DeviceWindow

---

---

Cache  
View

Cache usage priority (button)  
DeviceWindow

cache, delete  
MainWindow

cache, move  
MainWindow

cache, protect  
MainWindow

cache-programs, other  
Known Bugs

Cancel (button)  
MainWindow

capacity  
InfoWindow

Cash  
Registration

change floppy  
Concepts

Checksum error <1>  
New Bug

Checksum error <2>  
Known Bugs

Checksum error  
History

checksummes (button)  
MainWindow

Chipmemory <1>  
TurboBoards

Chipmemory  
MainWindow

CloseDevice  
Known Bugs

color flash  
MainWindow

color flash (button)  
MainWindow

---

---

- CompactDisk
  - Features
- Compatibility
  - Features
- concepts
  - Concepts
- Contac addresses
  - Author
- Convert
  - Other Products
- Copper
  - Other Products
- copy
  - Benchmarks
- CopyMem(Quick) (OS) <1>
  - Requirements
- CopyMem(Quick) (OS) <2>
  - Known Bugs
- CopyMem(Quick) (OS)
  - Speed up
- Copyright
  - Copyright
- Create
  - View
- Credit cards
  - Registration
- Credits
  - Credits
- CrossDOSFileSystem(MSD)
  - Features
- CSPPC
  - Tested Systems
- CVPPC
  - Tested Systems
- CyberGuard <1>
  - New Bug
- CyberGuard
  - DebugFiles

---

---

DataSafety <1>  
DeviceWindow

DataSafety <2>  
Features

DataSafety  
DataSafety

Default  
Default

delete cache (button)  
MainWindow

Device  
DeviceWindow

Device Software <1>  
View

Device Software  
InfoWindow

Devices  
Requirements

DirOpus5 Magellan  
Tested Systems

disable (button)  
DeviceWindow

Disk name <1>  
InfoWindow

Disk name  
View

DiskExpander  
Features

DiskSafe <1>  
Features

DiskSafe <2>  
DeviceWindow

DiskSafe  
Requirements

DiskSpeed  
Benchmarks

Distribution  
Copyright

---



---

- DoIO (OS)
  - Programmers
- Dos-Buffers
  - Features
- Drive informations
  - DeviceWindow
- drives
  - MainWindow
- Drives (button)
  - MainWindow
- DynamiCache <1>
  - Registration
- DynamiCache
  - Known Bugs
- Elevator seeking
  - DeviceWindow
- EMail
  - Author
- Email, Free
  - Free Email
- enable (button)
  - DeviceWindow
- End (button)
  - View
- Enforcer <1>
  - Known Bugs
- Enforcer <2>
  - DebugFiles
- Enforcer
  - New Bug
- environment, saved
  - Concepts
- Eurocheque
  - Registration
- Exec library
  - Other Products
- factor
  - Benchmarks

---

---

- FastExec
  - TurboBoards
- FastFileSystem V43.20
  - SCSIdevice installation
- FastFileSystem V44.5
  - FileSystem installation
- FastFileSystem(FFS)
  - Features
- Fastmemory <1>
  - TurboBoards
- Fastmemory
  - MainWindow
- FAX, Free <1>
  - Free FAX
- FAX, Free
  - Registration
- Features
  - Features
- FFS
  - Features
- File Monitor
  - SCSIdevice installation
- FileSystems
  - Requirements
- first (button)
  - MainWindow
- First Track number <1>
  - InfoWindow
- First Track number
  - View
- Flags
  - View
- flexible
  - Concepts
- Floppy
  - Features
- FLUSH Cache (Argument)
  - View

---

---

- Font
  - History
- FROM (Argument) <1>
  - Preferences
- FROM (Argument)
  - Installation
- Full version
  - Registration
- Future
  - Future
- Future Copper Producer
  - Other Products
- Future Drive Accelerator
  - Features
- Guide
  - Benchmarks
- Guru
  - OS more reliable
- Guru-Alert
  - New Bug
- Gurunumbers
  - New Bug
- Hack
  - SCSIdevice installation
- hard disk
  - Features
- Harddisk, boot <1>
  - FileSystem installation
- Harddisk, boot
  - Speed up
- Hardware Cache
  - DeviceWindow
- hardware, less used
  - Concepts
- Hardware, UnitNo
  - InfoWindow
- HDOff
  - Installation

---

---

- HDToolsBox
  - FileSystem installation
- hierarchy
  - DeviceWindow
- History
  - History
- Homepage
  - Author
- HTTP
  - Author
- HyperCache
  - Registration
- IDE <1>
  - Features
- IDE
  - Tested Systems
- IF (Shell Command)
  - ReturnNumbers
- inactive
  - DeviceWindow
- Info (button)
  - DeviceWindow
- Installation
  - Installation
- Installer V43.3
  - Installation
- Instruction erros
  - OS more reliable
- KILL FDA (Argument)
  - View
- L: directory
  - FileSystem installation
- languages
  - Future
- leasing
  - Registration
- Legal Stuff
  - Copyright

---

---

LinUX  
  Other Products

LinUX Berkeley Fast FileSystem(BFFS UNI\\02)  
  Features

Location  
  View

LongWordAligned  
  Programmers

low memory  
  Concepts

Mail  
  Author

MainProgPath (Argument)  
  Preferences

Medium  
  View

memory  
  Requirements

Memory corrupt  
  OS more reliable

Memory Test  
  Mark Bad Memory

Memory type  
  View

Memory, Bad  
  Mark Bad Memory

MessyFileSystem (MSD)  
  Features

MMU <1>  
  DebugFiles

MMU  
  New Bug

Modification  
  View

Monitor  
  View

monitor  
  View

---

---

- move cache (button)
  - MainWindow
  
- MSDos
  - Features
  
- MultiCX
  - DebugFiles
  
- MultifaceIII
  - Tested Systems
  
- MungFriend
  - New Bug
  
- MungFriend After Reset-GURU
  - DebugFiles
  
- MungWall <1>
  - DebugFiles
  
- MungWall <2>
  - Known Bugs
  
- MungWall
  - New Bug
  
- Must Write
  - View
  
- nature, saved
  - Concepts
  
- NetBSD Berkeley Fast FileSystem(BFFS UNI\\02)
  - Features
  
- NewAlertH
  - SCSIdevice installation
  
- news
  - Concepts
  
- NewStyleDevice (NSD) <1>
  - Features
  
- NewStyleDevice (NSD) <2>
  - Technical
  
- NewStyleDevice (NSD)
  - InfoWindow
  
- Next Medium (button)
  - View
  
- NoRamReverse <1>
  - Installation

---

---

NoRamReverse  
Speed up

not used memory  
MainWindow

not used memory (button)  
MainWindow

Now Busy  
View

Number of Tracks  
InfoWindow

Oberon-2  
Technical

Oberon-2 (language)  
Future

Old  
View

only  
Registration

oo2c  
Future

Orders  
Registration

OS 2.0  
Requirements

overall requirements  
Requirements

Page down (button)  
View

Page up (button)  
View

Parti  
View

Partition  
View

PatchWork  
Known Bugs

Permission  
Copyright

---

---

PFS  
Features

Phone  
Registration

PicassoII  
Tested Systems

Picture  
Other Products

PoolMem <1>  
Speed up

PoolMem  
Installation

Postal address  
Author

power cut  
DataSafety

Power-LED  
Features

PowerCache <1>  
Registration

PowerCache  
Known Bugs

PowerPC  
Tested Systems

Preferences  
Preferences

ProfiFileSystem(PFS) <1>  
DataSafety

ProfiFileSystem(PFS) <2>  
Features

ProfiFileSystem(PFS)  
Future

Prohibition  
Copyright

protect cache (button)  
MainWindow

PS-2  
Mark Bad Memory

---



---

QNX  
Future

QUIET (Argument)  
Installation

quit  
View

read-ahead <1>  
DeviceWindow

read-ahead  
Features

Registration  
Registration

Removeable Disk? (button)  
DeviceWindow

Return values  
ReturnNumbers

RigidDiskBlock <1>  
Speed up

RigidDiskBlock  
FileSystem installation

S:Startup-Sequence  
Installation

SaferPatches  
Installation

Save (Argument)  
Preferences

Save (button)  
MainWindow

SCSI  
Features

SCSI (UW)  
Tested Systems

SCSI Device  
SCSIdevice installation

SCSI-2  
Tested Systems

SCSI-direct <1>  
Technical

---

---

- SCSI-direct
  - History
- SCSIsynchron-Flag
  - Speed up
- Seconds
  - Default
- SegTracker <1>
  - DebugFiles
- SegTracker
  - New Bug
- SendIO (OS)
  - Programmers
- set size
  - Concepts
- SetMan
  - Installation
- SetPatch
  - Installation
- SFS
  - Features
- ShareIt
  - Registration
- SIMM
  - Mark Bad Memory
- Size
  - View
- Size of Block
  - InfoWindow
- Size of Track
  - View
- Size of Track (button)
  - DeviceWindow
- Smart-Power-Technologie
  - Features
- SmartCache
  - Features
- SmartFileSystem(SFS) <1>
  - Features

---

---

SmartFileSystem(SFS)  
DataSafety

Software Cache  
DeviceWindow

Sorted by (button)  
View

speed  
Benchmarks

Stabl OS  
OS more reliable

Stack, overflow  
OS more reliable

Stack, Supervisor  
TurboBoards

StackAttack  
OS more reliable

start position <l>  
InfoWindow

start position  
View

Static  
Mark Bad Memory

statistics  
Benchmarks

Student  
Registration

supported devices  
Features

supported FileSystems  
Features

Sushi <l>  
DebugFiles

Sushi  
New Bug

SysInfo  
Benchmarks

Systeme  
Tested Systems

---

---

TeX  
  Other Products

Thanks  
  Credits

time  
  Benchmarks

Time  
  Default

Tnt <1>  
  DebugFiles

Tnt  
  New Bug

Top (button)  
  View

Tower with Zorro II Databoard (Micronik)  
  Tested Systems

Track <1>  
  InfoWindow

Track  
  View

TrackDisk64 <1>  
  Technical

TrackDisk64  
  History

Umemployed  
  Registration

UNI\\02  
  Features

Unit number <1>  
  View

Unit number  
  InfoWindow

UPDATE Cache (Argument)  
  View

update command  
  DeviceWindow

URL  
  Author

---

---

Use (Argument)  
  Preferences

Use (button)  
  MainWindow

Used  
  View

uses free memory  
  Concepts

validate  
  DataSafety

vdisk.device (VD0:)  
  Known Bugs

Verify  
  Technical

Verify write  
  DeviceWindow

Verify write (button)  
  DeviceWindow

ViNCeD  
  Known Bugs

Virtual name  
  View

Virtual-Memory-Manager (VMM)  
  Known Bugs

Virtual-Memory-Manger (VMM)  
  Features

WBStartup directory  
  Installation

Windows <1>  
  Preferences

Windows  
  View

World Wide Web <1>  
  Registration

World Wide Web  
  Author

Worldwide  
  Registration

---

---

Write async (button) <1>  
    DataSafety

Write async (button)  
    DeviceWindow

Write for temporary (button)  
    DeviceWindow

Write late as possible (button)  
    DeviceWindow

Write retention  
    DeviceWindow

Write sync (button) <1>  
    DataSafety

Write sync (button)  
    DeviceWindow

Write through (button)  
    DeviceWindow

XFH  
    Features

ZIP  
    Features

---