

@ DLTEST-2 Master Print Mode Command ESC '!' n

7 6 5 4 3 2 1 0 --- Single bit numbers ----
U I X B E C P F Interpretation of bits in n

0 0 0 0 0 0 0 0 Set Pitch to Pica = 10 cpi
0 0 0 0 0 0 0 1 ☉Set Pitch to Elite = 12 cpi
0 0 0 0 0 0 1 0 ☪Set Proportional font on
0 0 0 0 0 1 0 0 ◆Set Condensed Pitch = 17 or 20 cpi
0 0 0 0 1 0 0 0 Set Emphasized printing on
0 0 0 1 0 0 0 0 ▶Set Boldface printing on
0 0 1 0 0 0 0 0 xexpand to 5 or 6 cpi
0 1 0 0 0 0 0 0 Switch to ITALIC characters
1 0 0 0 0 0 0 0 ÇEnable Underlining

7 6 5 4 3 2 1 0 ----- Sample Combinations -----
U I X B E C P F Interpretation of bits in n

0 0 0 0 0 0 0 0 = Pica Fixd Upright = Master Mode 0
0 0 0 0 0 0 1 0 = ☉Pica Prop Upright = Master Mode 2
0 0 0 0 0 1 0 0 = ◆Pica Fixd Cond Upright = Master Mode 4
0 0 0 0 0 1 1 0 = ♠Pica Prop Cond Upright = Master Mode 6
0 0 0 1 0 0 0 0 = ▶Pica Fixd Bold Upright = Master Mode 16
0 0 0 1 0 0 1 0 = †Pica Prop Bold Upright = Master Mode 18
0 0 0 1 0 1 0 0 = ¶Pica Fixd Cond Bold Upright = Master Mode 20
0 0 0 1 0 1 1 0 = ■Pica Prop Cond Bold Upright = Master Mode 22

0 1 0 0 0 0 0 0 = Pica Fixd Italic = Master Mode 64
0 1 0 0 0 0 1 0 = Pica Prop Italic = Master Mode 66
0 1 0 0 0 1 0 0 = Pica Fixd Cond Italic = Master Mode 68
0 1 0 0 0 1 1 0 = Pica Prop Cond Italic = Master Mode 70
0 1 0 1 0 0 0 0 = Pica Fixd Bold Italic = Master Mode 80
0 1 0 1 0 0 1 0 = Pica Prop Bold Italic = Master Mode 82
0 1 0 1 0 1 0 0 = Pica Fixd Cond Bold Italic = Master Mode 84
0 1 0 1 0 1 1 0 = Pica Prop Cond Bold Italic = Master Mode 86

0 0 0 0 0 0 0 1 = ☉Elite Fixd Upright = Master Mode 1
0 0 0 0 0 0 1 1 = ♥Elite Prop Upright = Master Mode 3
0 0 0 0 0 1 0 1 = ♣Elite Fixd Cond Upright = Master Mode 5
0 0 0 0 0 1 1 1 = Elite Prop Cond Upright = Master Mode 7
0 0 0 1 0 0 0 1 = ◀Elite Fixd Bold Upright = Master Mode 17
0 0 0 1 0 0 1 1 = !!Elite Prop Bold Upright = Master Mode 19
0 0 0 1 0 1 0 1 = \$Elite Fixd Cond Bold Upright = Master Mode 21
0 0 0 1 0 1 1 1 = †Elite Prop Cond Bold Upright = Master Mode 23

0 1 0 0 0 0 0 1 = Elite Fixd Italic = Master Mode 65
0 1 0 0 0 0 1 1 = Elite Prop Italic = Master Mode 67
0 1 0 0 0 1 0 1 = Elite Fixd Cond Italic = Master Mode 69
0 1 0 0 0 1 1 1 = Elite Prop Cond Italic = Master Mode 71
0 1 0 1 0 0 0 1 = Elite Fixd Bold Italic = Master Mode 81
0 1 0 1 0 0 1 1 = Elite Prop Bold Italic = Master Mode 83
0 1 0 1 0 1 0 1 = Elite Fixd Cond Bold Italic = Master Mode 85
0 1 0 1 0 1 1 1 = Elite Prop Cond Bold Italic = Master Mode 87

