

# Expert

The Expert Panel allows you to control a few features which may need to be adjusted in special situations. In most cases you can just leave these settings alone.

## Don't Eject Floppy on Restart

Normally, floppy diskettes are ejected whenever you start up or restart a Macintosh. When this box is checked, CDU will check any diskette in a floppy drive for a System and Finder. If it finds one, it will use that System instead of ejecting the floppy.

If this box is not checked, the floppy will be ejected as usual.

## Don't Eject SCSI on Restart

Normally, removable SCSI devices (like CD-ROMs or Syquest cartridges ) are always ejected when you start up or restart a Macintosh. When this box is checked, CDU will check any removable SCSI drive for a System and Finder. If it finds one, it will use that System instead of ejecting the SCSI device.

If this box is not checked, the SCSI device will be ejected as usual.

## AppleTalk Always Available

When this box is checked, AppleTalk is always loaded at startup. This allows you to turn AppleTalk on and off without restarting.

## Sound Level, Monitor Color Level, Desktop Pattern

If you leave these boxes checked, whenever you switch sets the sound level, monitor color level, and desktop pattern will switch to the new set's setting.

Whether these three boxes are checked or unchecked, you can set the sound level and monitor color level using the CDU Menu. You can modify the desktop pattern by using the General control panel of System 7 or the Desktop Patterns control panel of System 7.5.

#### Startup Bypass Key

Most extensions can be disabled by holding down some key during startup. CDU is set up to be turned off when you hold down the “~” (Tilde) key.

If you press the Tilde key after you turn on the power, or select Restart, you will see the CDU icon appear during booting with an X through it. Once you see this you can release the Tilde key.

You might want to change this to a different key if the Tilde key turns off something else that you want to be able to use. To change the key, select the long box under “Startup Bypass Key” and type the key you want to use.

#### Hot Key for This Set

This is a Hot Key combination that opens a specific set (for example, Energy Star on). To create a key combination, select the long box. Then type the combination you prefer to use.